

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = -\frac{1}{R \cdot C} \int U_E(t) dt + U_{A0}$	insert sine function	$U_E(t) = U_E \sin(\omega t)$
$U_A = -\frac{1}{R \cdot C} \int \sin(\omega t) dt + U_{A0}$	insert root function with limits	$\int \sin(ax) dx = -\frac{1}{a} \cos(ax)$
$U_A = -\frac{1}{R \cdot C} \int \cos(\omega t) dt + U_{A0}$	put constant before integral	
$U_A = \frac{1}{\omega R \cdot C} \int \cos(\omega t) dt + U_{A0}$	insert limits	$t_0=0, t_1=t$
$U_A = \frac{1}{\omega R \cdot C} [\sin(\omega t)]_0^t + U_{A0}$	$\cos(0) = 1$	
$U_A = \frac{1}{\omega R \cdot C} \sin(\omega t) + U_{A0}$	multiply	
$U_A = \frac{1}{\omega R \cdot C} \sin(\omega t) + U_{A0}$	consider the non-cosine terms	
$U_A = \frac{1}{\omega R \cdot C} \sin(\omega t) + U_{A0}$	This part is independent in time. Since we assume purely sinusoidal quantities, the for the initial voltage of the capacitor must be:	$U_{C0} = U_{A0} = \frac{1}{\omega R \cdot C} \sin(\omega t)$
$U_A = \frac{1}{\omega R \cdot C} \sin(\omega t) + U_{A0}$		
$U_A = \frac{1}{\omega R \cdot C} \sin(\omega t) + U_{A0}$		

From: <https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1632539851

Last update: 2021/09/25 05:17

