

# task\_nyniewamxfshpuwt\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E25 Resonant Circuit (written test, approx. 4 % of a 120-minute written test, SS2021) .....	2
--	---

resonance, resonant circuit, RMS, exam ee2 SS2021

**Exercise E25 Resonant Circuit**  
**(written test, approx. 4 % of a 120-minute written test, SS2021)**

6) An alternating current source with the effective voltage  $U_{\text{eff}} = 12 \text{ V}$  is connected in series with a resistor  $R_i = 200 \text{ m}\Omega$  and a capacitor  $C = 30 \text{ nF}$ . The resistance  $R$  can be varied. The voltage  $U_C$  across the capacitor is measured. The resonance frequency  $f_0$  is determined by the condition  $U_C = U_{\text{eff}}$ .

- $U_{\text{eff}} = 12 \text{ V} \cdot \sin(2\pi \cdot f_0 \cdot t)$

Path:  $R_i = 200 \text{ m}\Omega$

$$R_i = 200 \text{ m}\Omega$$

- $C = 30 \text{ nF}$

For the following calculation, the internal resistance  $R_i$  and the resistance  $R$  have to be combined:  $R_{\Sigma} = R_i + R$

Here, either one knows that the gain factor  $Q$  stands for  $Q = \frac{U_C}{U_{\text{eff}}}$  and therefore can directly use the following formula:  $Q = \frac{U_C}{U_{\text{eff}}} = \frac{1}{R_{\Sigma}} \sqrt{\frac{L}{C}}$   
 $R_{\Sigma} = \frac{U_{\text{eff}}}{U_C} \sqrt{\frac{L}{C}}$

When the gain factor is not known, one has to derive it:

The voltage  $U$  at resonance is only given by the total ohmic resistance  $R_{\Sigma}$  and the source voltage  $U_{\text{eff}}$ :  $I = \frac{U_{\text{eff}}}{R_{\Sigma}}$

This current flow also through the impedance of the capacitor  $Z_C = \frac{1}{\omega C}$   
 $U_C = Z_C \cdot I = \frac{1}{\omega C} \cdot \frac{U_{\text{eff}}}{R_{\Sigma}}$

At resonance, the angular frequency  $\omega$  is given by  $\omega = \frac{1}{\sqrt{LC}}$

$$U_C = \frac{U_{\text{eff}}}{\frac{1}{\sqrt{LC}} R_{\Sigma}} = \frac{U_{\text{eff}} \sqrt{LC}}{R_{\Sigma}}$$

a) What is the resonance frequency  $f_0$ ?

Path

In both cases, we end up with the same formula, where we have to insert the physical values:  $R_{\Sigma} = \frac{U_{\text{eff}}}{U_C} \sqrt{\frac{L}{C}}$   
 $R_{\Sigma} = \frac{12 \text{ V}}{12 \text{ V}} \sqrt{\frac{20 \cdot 10^{-3} \text{ H}}{30 \cdot 10^{-6} \text{ F}}} = 200 \text{ m}\Omega$

The resonant frequency  $f_0$  is given as  $f_0 = \frac{1}{2\pi \sqrt{LC}}$

And so, the resistance  $R$  is:  $R = R_{\Sigma} - R_i$

$$R = 200 \text{ m}\Omega - 200 \text{ m}\Omega = 0 \text{ m}\Omega$$

From:

<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

[https://first.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_nyniewamxfshpuwt\\_with\\_calculation](https://first.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_nyniewamxfshpuwt_with_calculation)

Last update: **2024/07/04 03:52**

