

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E5 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	3
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	6
Exercise E9 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	7
Exercise E13 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	7
Exercise E11 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	11
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	11
Exercise E7 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	12
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	13
Exercise E6 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	15
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	19
Exercise E10 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	20
Exercise E14 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	20
Exercise E12 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	24
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	24
Exercise E8 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,	


WS2022)	25
Exercise E4 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	26

start

**Exercise E5 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result

$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \text{ } \Omega \end{aligned}$$



Calculated the internal resistance R_{i} and the source voltage U_{rs} of an equivalent linear voltage source on the connectors A and B . $R_1=5.0 \text{ } \Omega$, $U_2=6.0 \text{ V}$, $R_3= 10 \text{ } \Omega$, $I_4=4.2 \text{ A}$, $R_5=10 \text{ } \Omega$, $R_6=7.5 \text{ } \Omega$, $R_7=15 \text{ } \Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} - (U_2 \over R_1 - I_4) \cdot R_1 || R_3 || R_5$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \Omega \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega}$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

endstart

Exercise E2 Temperature-dependent Resistance
(written test, approx. 6 % of a 60-minute written test, WS2022)

2. The graph shows the temperature dependence of the resistance of a resistor. The resistor has a resistance of $10 \text{ k}\Omega$ at 25°C . Calculate the resistance of the thermistor at -40°C .

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$.

The temperature inside the refrigeration system can reach down to -40°C .

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

Resistance of the resistor R depends on the temperature T and the heat Q . Therefore, a solution is to use a heat pump to heat up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

with $\Delta T = T_{\text{end}} - T_{\text{start}}$

$$R = 10 \text{ k}\Omega \cdot (1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

endstart

Exercise E9 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phasor voltage \underline{u} (in V) at $t = 30$ ms for the circuit shown in the figure. The components R and X_L shall be given.

After analysis, the following phasor voltage \underline{u} is extracted: $\underline{u} = 48.2 \angle -19.8^\circ$ V. In the time domain, the voltage is $u(t) = 48.2 \sqrt{2} \cos(2\pi \cdot 15 \cdot t - 19.8^\circ)$ V.

Solution
.. Calculate the physical values of the components.
Solution $R = 10 \Omega$, $X_L = 20 \Omega$

Solution
$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{10 + j20} = 2.5 \angle -63.4^\circ$$

The current and voltage are in phase since the circuit is purely resistive.
The voltage across the capacitor is $\underline{u}_C = \underline{I} \cdot (-j20) = 50 \angle -63.4^\circ - 90^\circ = 50 \angle -153.4^\circ$ V.
The voltage across the inductor is $\underline{u}_L = \underline{I} \cdot j20 = 50 \angle -63.4^\circ + 90^\circ = 50 \angle 26.6^\circ$ V.
The total voltage is $\underline{u} = \underline{u}_C + \underline{u}_L = 50 \angle -153.4^\circ + 50 \angle 26.6^\circ = 48.2 \angle -19.8^\circ$ V.
With the complex part comes the complex value $\underline{u} = 48.2 \angle -19.8^\circ$ V.
 $\varphi = \arctan\left(\frac{\text{Im}(\underline{u})}{\text{Re}(\underline{u})}\right) = \arctan\left(\frac{-16.5}{48.2}\right) = -19.8^\circ$
The phase φ can be calculated as $\varphi = \arctan\left(\frac{-4.68}{0.24}\right) = -10.8^\circ$

endstart

Exercise E13 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the resulting phasor voltage \underline{u} (in V) at $t = 30$ ms for the circuit shown in the figure. The components R and X_L shall be given. The voltage source is $u(t) = 3.0 \sqrt{2} \cos(2\pi \cdot 15 \cdot t - 19.8^\circ)$ V. The circuit consists of a resistor of 10Ω , an inductor of $330 \mu\text{H}$, and a capacitor of $22 \mu\text{F}$, all in series.


Solution
Result
.. Draw the circuit diagram of the given circuit. Label all components, voltages, and currents.
Solution $Z = 10 + j19.8 - j48.2 = 10 - j28.4 \Omega$

```

\begin{align*} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi \cdot f \cdot C} \quad \omega = 2\pi \cdot 15 \\
\omega &= 2\pi \cdot 15 \cdot 10^{-3} = 942 \text{ rad/s} \\
\begin{align*} I &= \frac{U}{Z} = \frac{10 \text{ V}}{\sqrt{R^2 + (Z_L - Z_C)^2}} \\
&= \frac{10}{\sqrt{30^2 + (19.28 - 0.02)^2}} \\
&= 0.33 \text{ A} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi \cdot f \cdot C} \quad \omega = 2\pi \cdot 15 \\
&\approx 109 \text{ } \Omega \\
\begin{align*} \underline{Z} &= R + j \underline{Z}_L - j \underline{Z}_C \\
&= 30 + j(19.28 - 109) \\
&= 30 - j89.72 \\
|\underline{Z}| &= \sqrt{30^2 + 89.72^2} \approx 94.2 \text{ } \Omega
\end{align*}
\end{align*}

```

□□□□□□□□ □510...



endstart

Exercise E11 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_1
 Budget in the parallel circuit: $V = I \cdot Z$ since V and I are perpendicular
 $V = I \cdot \sqrt{R_2^2 + X_C^2}$ since V and I are perpendicular
 $I = \frac{V}{\sqrt{R_2^2 + X_C^2}}$ (It has to, since R_3 is perpendicular to Z)
 $I^2 = \frac{V^2}{R_2^2 + X_C^2}$
 Therefore the resulting current of the parallel circuit is given as:
 $I_{3R} = I_{3C} + I_{3L}$
 $I_{3R} = \frac{V}{\sqrt{R_2^2 + X_C^2}} + \frac{V}{R_3}$
 $I_{3R} = \frac{V}{60 \text{ mA}}$
 $\left(\frac{V}{60 \text{ mA}}\right)^2 = \left(\frac{V}{\sqrt{R_2^2 + X_C^2}} + \frac{V}{R_3}\right)^2$
 Back to the first formula: $R_3 \cdot I_{3R} = X_C \cdot I_{3C}$
 $R_3 = X_C \cdot \frac{I_{3C}}{I_{3R}}$
 $R_3 = \frac{1}{2\pi \cdot f \cdot C_3} \cdot \frac{\sqrt{R_2^2 + X_C^2}}{R_3}$

Solution

$R_1 = 1.00 \text{ } \Omega$

$R_2 = 10.0 \text{ } \Omega$

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_1 and C_1
 Budget in the parallel circuit: $V = I \cdot Z$ since V and I are perpendicular
 $V = I \cdot \sqrt{R_2^2 + X_C^2}$ since V and I are perpendicular
 $I = \frac{V}{\sqrt{R_2^2 + X_C^2}}$ (It has to, since R_3 is perpendicular to Z)
 $I^2 = \frac{V^2}{R_2^2 + X_C^2}$
 Therefore the resulting current of the parallel circuit is given as:
 $I_{3R} = I_{3C} + I_{3L}$
 $I_{3R} = \frac{V}{\sqrt{R_2^2 + X_C^2}} + \frac{V}{R_3}$
 $I_{3R} = \frac{V}{60 \text{ mA}}$
 $\left(\frac{V}{60 \text{ mA}}\right)^2 = \left(\frac{V}{\sqrt{R_2^2 + X_C^2}} + \frac{V}{R_3}\right)^2$
 Back to the first formula: $R_3 \cdot I_{3R} = X_C \cdot I_{3C}$
 $R_3 = X_C \cdot \frac{I_{3C}}{I_{3R}}$
 $R_3 = \frac{1}{2\pi \cdot f \cdot C_3} \cdot \frac{\sqrt{R_2^2 + X_C^2}}{R_3}$

endstart

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

The heating element is used to heat the wire with a temperature of $180 \text{ } ^\circ\text{C}$.
 Result: power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.
 Distribute the current in the circuit for heating elements.
 The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .
 Solution: $R = 10.3 \text{ } \Omega$

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{l}{d^2 \cdot \pi} \quad | \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

endstart

Exercise E7 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real battery) also takes into account the internal resistance r of the battery. The voltage across the capacitor is again $U_c(t_0) = 0 \text{ V}$ at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution
 Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and r .


Solution
 The ideal voltage source U is in series with the internal resistance r and the resistor R_1 . The voltage across the capacitor is $u_c(t) = U \cdot (1 - e^{-t/\tau})$, where $\tau = (R_1 + r) \cdot C$.
 On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .



The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ } \Omega$ and a capacitor of $C = 100 \text{ } \mu\text{F}$.
 The switch S_2 to an additional consumer R_2 will be considered to be open for the first asks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

- 1. First do not consider the light bulb - it is not connected to the RC circuit.
- 2. Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_C(t_1) = 0.5 \cdot U$:

$$u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5 \Rightarrow e^{-t/\tau} = 0.5 \Rightarrow -t/\tau = \ln(0.5) \Rightarrow t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \Omega$, short-circuit).
 $R_i = R_1 \parallel R_B = 10 \Omega$

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ms} / (10 \Omega \cdot 100 \mu\text{F})})$$


endstart

Exercise E3 Pure Resistor Network Simplification
 (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at 20°C. On the left, $R_1 = R_2 = R_3 = 10 \Omega$ and the voltage source $U = 10 \text{V}$. The result is given in R_B .

Solution

$R_2 = R_3 = 100 \Omega$



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:

$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$


The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = R_Y + (R_Y + R_1) \parallel (R_Y + R_2) \parallel R_4$$

$$= 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:


$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

endstart

**Exercise E6 Equivalent linear Source
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.
Result

$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculated the internal resistance R_{int} and the source voltage U_{oc} of an equivalent linear voltage source on the connectors A and B .
$$R_1=5.0 \text{ } \Omega, \quad U_2=6.0 \text{ V}, \quad R_3= 10 \text{ } \Omega, \quad I_4=4.2 \text{ A}, \quad R_5=10 \text{ } \Omega, \quad R_6=7.5 \text{ } \Omega, \quad R_7=15 \text{ } \Omega$$
 Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot (R_6 || R_7)$$

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left(\frac{U_2}{R_1} - I_4 \right) \cdot R_1 || R_3 || R_5$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \left(\frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot 15 \Omega \cdot 2.5 \Omega \cdot \frac{1}{7.5 \Omega + 15 \Omega + 2.5 \Omega}$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

endstart

Exercise E2 Temperature-dependent Resistance
(written test, approx. 6 % of a 60-minute written test, WS2022)

2. The diagram shows a circuit with a temperature-sensitive resistor. The resistor has a resistance of $10 \text{ k}\Omega$ at 25°C . Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$. Calculate the resistance of the thermistor at -40°C .

Result: $R = 6.5 \text{ k}\Omega$

The temperature inside the refrigeration system can reach down to -40°C . Calculate the resistance of the thermistor at -40°C .

Resistance of the resistor R depends on the temperature T and the heat Q . Therefore, a solution is to use a heat pump up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

with $\Delta T = T_{\text{end}} - T_{\text{start}}$

$$R = 10 \text{ k}\Omega \cdot \left(1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$


```

\begin{align*} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi f C} \quad \omega = 2\pi \cdot 15 \\
\omega &= 2\pi \cdot 15 \cdot 10^{-3} = 94.2 \text{ rad/s} \\
\begin{align*} I &= \frac{U}{Z} = \frac{10 \text{ V}}{\sqrt{R^2 + \left(\frac{1}{\omega C}\right)^2}} \\
&= \frac{10}{\sqrt{30^2 + \left(\frac{1}{94.2 \cdot 10^{-6}}\right)^2}} \\
&= 19.28 \text{ mA} \quad \omega = 19.28 \cdot 2\pi \\
\end{align*}
\begin{align*} Z_C &= \frac{1}{2\pi f C} \quad \omega = 2\pi \cdot 15 \\
&\sim 330 \text{ kHz} \cdot 330 \text{ }\mu\text{H} \\
\end{align*}
\begin{align*} \underline{Z} &= R + \underline{Z}_L + \underline{Z}_C \quad \underline{Z} = R + j \\
&\cdot Z_L - j \cdot Z_C \quad \underline{Z} = R + j \cdot (Z_L - Z_C) \\
|\underline{Z}| &= \sqrt{R^2 + (Z_L - Z_C)^2} \\
\end{align*}

```

□□□□□□□□ □510...



endstart

Exercise E12 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit with a resistor $R_1 = 1.00 \text{ k}\Omega$ and a capacitor $C_1 = 40 \text{ nF}$ is connected to an AC voltage source $U = 10 \text{ V}$ at a frequency $f = 4 \text{ MHz}$. The current I through the resistor R_1 shall have the same absolute value of the impedance as a capacitor $C_2 = 10 \text{ nF}$ at a frequency $f = 10 \text{ MHz}$.

Solution

$$R_1 = 1.00 \text{ k}\Omega$$

$$R_2 = 10.0 \text{ k}\Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R_1 and C_1 combined is given by

$$Z_{R_1C_1} = \sqrt{R_1^2 + X_{C_1}^2}$$

where $X_{C_1} = \frac{1}{\omega C_1}$ is the capacitive reactance.

For the capacitor C_2 at frequency $f_2 = 10 \text{ MHz}$, the reactance is

$$X_{C_2} = \frac{1}{\omega_2 C_2}$$

The condition is that the absolute value of the impedance of the series circuit $Z_{R_1C_1}$ is equal to the reactance X_{C_2} .

$$\sqrt{R_1^2 + \left(\frac{1}{\omega C_1}\right)^2} = \frac{1}{\omega_2 C_2}$$

Squaring both sides and rearranging:

$$R_1^2 + \frac{1}{\omega^2 C_1^2} = \frac{1}{\omega_2^2 C_2^2}$$

$$R_1^2 = \frac{1}{\omega_2^2 C_2^2} - \frac{1}{\omega^2 C_1^2}$$

Substituting the values:

$$R_1^2 = \frac{1}{(4 \cdot 10^6)^2 \cdot (10 \cdot 10^{-9})^2} - \frac{1}{(4 \cdot 10^6)^2 \cdot (40 \cdot 10^{-9})^2}$$

$$R_1^2 = \frac{1}{16 \cdot 10^{12} \cdot 10^{-18}} - \frac{1}{16 \cdot 10^{12} \cdot 1600 \cdot 10^{-18}}$$

$$R_1^2 = \frac{1}{16 \cdot 10^{-6}} - \frac{1}{256 \cdot 10^{-6}}$$

$$R_1^2 = \frac{1}{16} \cdot 10^6 - \frac{1}{256} \cdot 10^6$$

$$R_1^2 = \left(\frac{16}{16} - \frac{1}{256}\right) \cdot 10^6$$

$$R_1^2 = \left(\frac{255}{256}\right) \cdot 10^6$$

$$R_1 = \sqrt{\frac{255}{256} \cdot 10^6} \approx 999.6 \text{ }\Omega \approx 1.00 \text{ k}\Omega$$

endstart

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of nichrome wire with a diameter of $d = 0.357 \text{ mm}$ and a length of $l = 3 \text{ m}$ is used. The power dissipation $P = 40 \text{ W}$ is necessary. Calculate the resistance R of the heating element.

Solution

$$R = \frac{U^2}{P}$$

$$R = \frac{(10 \text{ V})^2}{40 \text{ W}} = 2.5 \text{ }\Omega$$

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{l}{d^2 \cdot \pi} \quad | \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$


endstart

Exercise E8 Charging Capacitors
(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the real battery) also takes into account the internal resistance of the battery. The voltage across the capacitor is again $U_c(t_0) = 0 \text{ V}$ at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution
Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

Solution
The ideal voltage source U is in series with the internal resistance R_1 and the external resistance R_2 . The voltage across the capacitor is $u_c(t) = U \cdot (1 - e^{-t/\tau})$, where $\tau = (R_1 + R_2) \cdot C$.
On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ } \Omega$ and a capacitor of $C = 100 \text{ } \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first asks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

- .. First do not consider the light bulb - it is not connected to the RC circuit.
- Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_C(t_1) = 0.5 \cdot U$:

$$u_C(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5 \Rightarrow e^{-t/\tau} = 0.5 \Rightarrow -t/\tau = \ln(0.5) \Rightarrow t = \tau \cdot \ln(0.5)$



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \Omega$, short-circuit).
 $R_i = R_1 \parallel R_B = 10 \Omega$

$$u_C(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1 \text{ms} / (10 \Omega \cdot 100 \mu\text{F})})$$


endstart

Exercise E4 Pure Resistor Network Simplification
 (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved at 0°C. On the left, $R_1 = R_2 = R_3 = 10 \Omega$ and $R_4 = R_5 = 20 \Omega$ are given. $R_6 = 10 \Omega$ and the source $U = 10 \text{V}$ are given. R_B .

Solution

$R_2 = R_3 = 100 \Omega$



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \cdot 200 \sim \Omega\} \over {500 \sim \Omega + 200 \sim \Omega}$$

end

From: <https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680091981

Last update: 2023/03/29 14:13

