

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

- Exercise E5 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 3
- Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 6
- Exercise E9 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 7
- Exercise E13 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 7
- Exercise E11 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 10
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 10
- Exercise E7 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) ..... 11
- Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) ..... 12
- Exercise E6 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 14
- Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 18
- Exercise E10 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 19
- Exercise E14 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 19
- Exercise E12 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 22
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 22
- Exercise E8 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,

WS2022) ..... 23

Exercise E4 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute  
written test, WS2022) ..... 24





The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_{24}}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \text{ A} \cdot 15 \Omega \cdot 2.5 \Omega \cdot \frac{1}{7.5 \Omega + 15 \Omega + 2.5 \Omega}$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator is explained with the effect of resistance on refrigeration system. The refrigerator has a resistance of  $10 \Omega$  at  $25^\circ \text{C}$  and  $25 \Omega$  at  $-40^\circ \text{C}$ .

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

**Result** The temperature inside the refrigeration system can reach down to  $-40^\circ \text{C}$ .

$$R = 10 \cdot (1 + 0.01 \cdot \Delta T + 71 \cdot 10^{-6} \cdot \Delta T^2)$$

The power transfer is  $P = U \cdot I = \frac{U^2}{R}$ . Therefore, a solution is to use a heat pump to heat the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \Omega \cdot \left( 1 + 0.01 \cdot (-40^\circ \text{C} - 25^\circ \text{C}) + 71 \cdot 10^{-6} \cdot (-40^\circ \text{C} - 25^\circ \text{C})^2 \right)$$

**Exercise E9 Analyzing complex Impedances**  
 (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex power  $\underline{S}$  and the real power  $P$  in the circuit shown in the figure. The voltage  $\underline{u}$  and the current  $\underline{i}$  shall be given.

After analysis, the following complex power  $\underline{S}$  and real power  $P$  shall be extracted and given in the table below. The voltage  $\underline{u}$  and the current  $\underline{i}$  shall be given in the table below.

Solution
.. Calculation of the physical values of the two components.
Solution $\underline{R} = 10 \Omega \quad \underline{X}_L = j 2 \pi \cdot 50 \text{ Hz} \cdot 0,02 \text{ H} = j 6,28 \Omega$
Solution
$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \text{ V}}{10 \Omega + j 6,28 \Omega} = \frac{50}{12,5} \cdot \frac{1}{1 + j 0,628} = 4 \cdot \frac{1}{1 + j 0,628}$
The voltage $\underline{u}$ and the current $\underline{i}$ shall be given in the table below.
resulting impedance $\underline{Z} = 10 \Omega + j 6,28 \Omega$
Therefore, the complex power $\underline{S}$ shall be calculated as $\underline{S} = \underline{U} \cdot \underline{I}^*$
$\underline{S} = 50 \text{ V} \cdot \frac{4}{1 + j 0,628} = \frac{200}{1 + j 0,628} = \frac{200}{1 + j 0,628} \cdot \frac{1 - j 0,628}{1 - j 0,628} = \frac{200(1 - j 0,628)}{1 + 0,394} = \frac{200(1 - j 0,628)}{1,394}$
The real power $P$ shall be calculated as $P = \text{Re}(\underline{S})$
$P = \frac{200}{1,394} = 143,8 \text{ W}$
With the complex power $\underline{S}$ and the real power $P$ shall be calculated as $\underline{S} = P + j Q$
$\underline{S} = 143,8 \text{ W} + j 92,5 \text{ var}$
The phase $\varphi$ shall be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{S})}{\text{Re}(\underline{S})}\right) = \arctan\left(\frac{92,5}{143,8}\right) = 32,5^\circ$

**Exercise E13 Complex Impedance Circuit**  
 (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the complex power  $\underline{S}$  and the real power  $P$  in the circuit shown in the figure. The voltage  $\underline{u}$  and the current  $\underline{i}$  shall be given. The voltage  $\underline{u}$  and the current  $\underline{i}$  shall be given in the table below.

Solution
Result
.. Draw the circuit diagram of the given circuit.
able all components, voltages, and currents.
$\underline{Z} = \frac{\underline{U}}{\underline{I}} = \frac{10 \text{ V}}{0,2 \text{ A}} = 50 \Omega$
$\underline{Z}_C = \frac{1}{j \omega C} = \frac{1}{j 2 \pi \cdot 15 \text{ kHz} \cdot 0,22 \mu\text{F}} = -j 1,59 \Omega$
Result $\underline{Z} = 50 \Omega - j 1,59 \Omega = 49,8 \Omega - j 1,59 \Omega$
With the complex power $\underline{S}$ and the real power $P$ shall be calculated as $\underline{S} = P + j Q$
$\underline{S} = 10 \text{ V} \cdot \frac{10 \text{ V}}{50 \Omega - j 1,59 \Omega} = \frac{100}{50 - j 1,59} = \frac{100(50 + j 1,59)}{2500 + 2,53} = \frac{100(50 + j 1,59)}{2502,53} = 3,99 \text{ W} + j 0,063 \text{ var}$
The phase $\varphi$ shall be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{S})}{\text{Re}(\underline{S})}\right) = \arctan\left(\frac{0,063}{3,99}\right) = 0,9^\circ$





**Exercise E11 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

**2. a) A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$ , a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ , and an AC voltage source with a voltage of  $U = 200 \text{ V}$  and a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance  $Z$  of the circuit.**

**Solution**

$$Z = \sqrt{R_1^2 + X_C^2}$$

$$Z = \sqrt{(1.00 \text{ k}\Omega)^2 + \left(\frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}\right)^2}$$

$$Z = \sqrt{(1.00 \text{ k}\Omega)^2 + (0.995 \text{ k}\Omega)^2}$$

$$Z = 1.41 \text{ k}\Omega$$

A series circuit means that the current is constant on every component. The equivalent impedance for  $R$  and  $X_C$  combined is given by  $Z = \sqrt{R^2 + X_C^2}$ . Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$ . 
$$\frac{1}{Z} = \frac{1}{R_1} + \frac{1}{R_2}$$
 Since  $U$  is perpendicular to  $R_2$ , this can be simplified to 
$$Z = \sqrt{R_1^2 + R_2^2}$$
 
$$Z = \sqrt{(1.00 \text{ k}\Omega)^2 + (0.995 \text{ k}\Omega)^2}$$
 
$$Z = 1.41 \text{ k}\Omega$$
 Therefore, the resulting current of the parallel circuit is given as: 
$$I = \frac{U}{Z} = \frac{200 \text{ V}}{1.41 \text{ k}\Omega} = 142 \text{ mA}$$
 This can be rearranged to 
$$Z = \frac{U}{I} = \frac{200 \text{ V}}{142 \text{ mA}} = 1.41 \text{ k}\Omega$$
 Back to the first formula: 
$$Z = \sqrt{R_1^2 + X_C^2}$$
 
$$Z^2 = R_1^2 + X_C^2$$
 
$$Z^2 - R_1^2 = X_C^2$$
 
$$Z = \sqrt{R_1^2 + X_C^2}$$

**Exercise E1 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

**2. For heating elements used to heat the oven at a temperature of  $180 \text{ }^\circ\text{C}$ , an electric power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary. Calculate the current  $I$  needed to operate the heating elements. The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$ .**

The heating element is  $l = 3 \text{ m}$  long and has a diameter of  $d = 3.57 \text{ mm}$ .

**Solution**

$$P = U \cdot I = R \cdot I^2 \rightarrow I = \sqrt{\frac{P}{R}}$$

**Solution**

$$P = U \cdot I = R \cdot I^2 \rightarrow I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} \cdot d^2 \cdot \pi \quad \& \quad \rho = \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E7 Charging Capacitors**  
**(written test, approx. 16 % of a 60-minute written test, WS2022)**

The circuit (with the light bulb) is a series of  $R_1$  and  $R_2$  and a capacitor  $C$  as indicated in Figure 1. The switch  $S_1$  is open. The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution:** To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

The ideal voltage source  $U$  is in series with  $R_1$  and  $R_2$ . The voltage  $u_c$  is independent of this series combination.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_1$ .




The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \Omega$  and a capacitor of  $C = 100 \mu\text{F}$ .

The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

**Solution**



An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R_1 = 0 \Omega$ , short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t_1) = 0.5 \cdot U$ : 
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$



**Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be simplified with  $R_1 = 200 \Omega$ ,  $R_2 = R_3 = 150 \Omega$ ,  $R_4 = 100 \Omega$  and the voltage  $U = 10 \text{ V}$ . Result:  $R_{eq}$ .

Solution

$$R_{eq} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as: 
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series: 
$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution




The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_{-1}) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel$$

**Exercise E6 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result

$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance  $R_i$  and the source voltage  $U_s$  of an equivalent linear voltage source on the connectors  $A$  and  $B$ .  
 $R_1 = 5.0 \Omega$ ,  $U_2 = 6.0 \text{ V}$ ,  $R_3 = 10 \Omega$ ,  $I_4 = 4.2 \text{ A}$ ,  
 $R_5 = 10 \Omega$ ,  $R_6 = 7.5 \Omega$ ,  $R_7 = 15 \Omega$   
 Use equivalent sources in order to simplify the circuit!

### Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ : 
$$R_{135} = R_1 || R_3 || R_5$$
 
$$I_{24} = I_2 - I_4$$
 The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following: 
$$U_{24} = I_{24} \cdot R_{34}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot (R_1 || R_3 || R_5)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot (15 \Omega \cdot 2.5 \Omega) / (7.5 \Omega + 15 \Omega + 2.5 \Omega)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator is explained with the effect of resistance on refrigeration systems. The refrigerant has a resistance of  $10 \Omega$  at  $25^\circ\text{C}$  and  $25 \Omega$  at  $-40^\circ\text{C}$ .

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

**Result** The temperature inside the refrigeration system can reach down to  $-40^\circ\text{C}$ .

$$R_{-40} = 10 \cdot (1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2) = 25 \Omega$$

The power transfer is  $P = U^2 / R$ . If the resistance  $R$  increases, the power  $P$  decreases. Therefore, a solution is to use a heat pump to heat the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \Omega \cdot \left( 1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2 \right)$$

### Exercise E10 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

1. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following dimensions must be provided:  $Z$  in  $\Omega$  and  $\varphi$  in degrees. The phase angle  $\varphi$  is defined as the phase shift of the current relative to the voltage.

Solution  
.. Calculate the physical values of the two components.  
Solution  $R = 10 \Omega$  and  $X_L = 2\pi \cdot 15 \cdot 0.01 = 0.942 \Omega$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \quad \text{with } \underline{U} = 3 \angle 0^\circ \text{ V and } \underline{I} = 0.24 \angle -\varphi \text{ A}$$

The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given. The resulting impedance  $Z$  is  $Z = \frac{U}{I} = \frac{3 \angle 0^\circ}{0.24 \angle -\varphi} = 12.5 \angle \varphi \Omega$ .

Therefore, the component  $R$  is  $R = |Z| \cdot \cos(\varphi) = 12.5 \cdot \cos(\varphi) \Omega$  and the component  $X_L$  is  $X_L = |Z| \cdot \sin(\varphi) = 12.5 \cdot \sin(\varphi) \Omega$ .

With the complex part  $Z = R + jX_L$  and  $Z = 12.5 \angle \varphi$  we get  $R = 12.5 \cdot \cos(\varphi)$  and  $X_L = 12.5 \cdot \sin(\varphi)$ .

The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{12.5 \cdot \sin(\varphi)}{12.5 \cdot \cos(\varphi)}\right) = \arctan(\tan(\varphi)) = \varphi$ .

With the complex part  $Z = R + jX_L$  and  $Z = 12.5 \angle \varphi$  we get  $R = 12.5 \cdot \cos(\varphi)$  and  $X_L = 12.5 \cdot \sin(\varphi)$ .

The phase  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{12.5 \cdot \sin(\varphi)}{12.5 \cdot \cos(\varphi)}\right) = \arctan(\tan(\varphi)) = \varphi$ .

.. Draw the circuit diagram of the given circuit and label all components, voltages, and currents.

Solution  $Z = 12.5 \angle \varphi \Omega$  and  $\varphi = 48.2^\circ$

Solution  $Z = 12.5 \angle 48.2^\circ \Omega$

### Exercise E14 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following dimensions must be provided:  $Z$  in  $\Omega$  and  $\varphi$  in degrees. The phase angle  $\varphi$  is defined as the phase shift of the current relative to the voltage.

Solution  
Result  $Z = 19.8 \angle 48.2^\circ \Omega$

.. Draw the circuit diagram of the given circuit and label all components, voltages, and currents.

Solution  $Z = 19.8 \angle 48.2^\circ \Omega$

Solution  $Z = 19.8 \angle 48.2^\circ \Omega$

Solution  $Z = 19.8 \angle 48.2^\circ \Omega$





**Exercise E12 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$  and a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ . The voltage across the resistor is  $U_{R_1} = 100 \text{ V}$  at a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance of the capacitor  $Z_C$  and the total impedance  $Z_{\text{total}}$  of the circuit.

**Solution**

$$Z_C = \frac{1}{j\omega C_1} = \frac{1}{j \cdot 2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = -j0.995 \text{ k}\Omega$$

$$Z_{\text{total}} = R_1 + Z_C = 1.00 \text{ k}\Omega - j0.995 \text{ k}\Omega$$

$$|Z_{\text{total}}| = \sqrt{1.00^2 + 0.995^2} \approx 1.41 \text{ k}\Omega$$

A series circuit means that the current is constant on every component. The equivalent impedance for  $R_1$  and  $Z_C$  combined is given by  $Z_{\text{total}}$ . Parallel circuit means that the voltage is the same on  $R_1$  and  $Z_C$ .  $U_{R_1} = U_{Z_C} = 100 \text{ V}$ . Since  $Z_C$  is perpendicular to  $R_1$ , the resulting current of the parallel circuit is given as:

$$I_{\text{total}} = I_{R_1} + I_{Z_C} = \frac{U_{R_1}}{R_1} + \frac{U_{Z_C}}{|Z_C|} = \frac{100}{1000} + \frac{100}{995} \approx 0.201 \text{ A}$$

Therefore, the resulting current of the parallel circuit is given as:

$$I_{\text{total}} = 0.201 \text{ A} = 201 \text{ mA}$$

**Exercise E1 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. For a heating element used to heat the oven at a temperature of  $180^\circ\text{C}$ , an electric power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary. Calculate the current  $I$  and the resistance  $R$  of the heating element. The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega\cdot\text{m}$ .

The heating element is  $l = 3 \text{ m}$  long and has a diameter of  $d = 3.57 \text{ mm}$ .

**Solution**

$$P = U \cdot I = R \cdot I^2 \quad \Rightarrow \quad I = \sqrt{\frac{P}{R}}$$

**Solution**

$$P = U \cdot I = R \cdot I^2 \quad \Rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E8 Charging Capacitors**  
**(written test, approx. 16 % of a 60-minute written test, WS2022)**

The circuit (with the light bulb) is a series of  $R_1$  and  $R_2$  and a capacitor  $C$  as indicated in Figure 8.5. Initially the switch  $S_1$  is open. The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution** To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

The ideal voltage source  $U$  is in series with  $R_1$  and  $R_2$ . The voltage  $u_c$  is independent of this series combination.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_2$ .




The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \Omega$  and a capacitor of  $C = 100 \mu\text{F}$ .

The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

**Solution**



An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R = 0 \Omega$ , short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t_1) = 0.5 \cdot U$ :  

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $t$ :  

$$(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$




**Exercise E4 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be solved at 0.10 A,  $R_1 = R_2 = R_3 = 1.5 \Omega$  and the voltage  $U = 10 \text{ V}$  is given.  $R_B$ .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.




Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as: 
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \text{ } \Omega)^2}{3 \cdot 100 \text{ } \Omega} = \frac{1}{3} \cdot 100 \text{ } \Omega = 33.33 \text{ } \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series: 
$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \text{ } \Omega + (33.33 \text{ } \Omega + 400 \text{ } \Omega) \parallel (33.33 \text{ } \Omega + 100 \text{ } \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = (500 \sim \Omega) \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \frac{500 \sim \Omega \cdot 200 \sim \Omega}{500 \sim \Omega + 200 \sim \Omega}$$

From:

<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

[https://first.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/ws2022\\_exam?rev=1680241422](https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680241422)

Last update: **2023/03/31 07:43**

