

Advanced simulations

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Advanced simulations

Junction Field Effect Transistor (JFET)

Digital Analogue Converter (DAC)

Time Domain - Frequency Domain

arbitrary periodic signals

2

2

2

3

3

Advanced simulations




Fig. 1: JFET Pinch Off

Junction Field Effect Transistor (JFET)

The structure of the junction field effect transistor (JFET) **resembles the bipolar transistor at first glance**. In [figure 1](#), the individual images (1)...(3) show the layering of an n-channel (English n-channel) JFET and the circuit symbol in the upper left. In contrast to the pnp bipolar transistor, however, here the p-doped layers are jointly supplied with voltage and the n-doped layer is transversely fluxed. Without voltage difference U_{GS} between gate and source, a (small) junction is formed at the p-n junctions. Electrons can flow unhindered through the n-doped layer: a current $I_G \gg 0$ flows through the FET ([figure 1 Fig. \(1\)](#)). The “path” between the two junction layers is called the n-channel.

Fig. 1: JFET Pinch Off 

When the voltage difference U_{GS} becomes smaller than zero, the junction layers increase, and the diode between G and S is operated in the reverse direction. The n-channel is constricted and geometrically decreases the electron or current flow I_G ([figure 1 Fig. \(2\)](#)). At a certain voltage $U_{GS} = U_p$ (pinch-off or pinch-off voltage), **the two junction layers are so large that no n-channel is left - the channel is pinched-off**** ([figure 1 figure \(3\)](#)). Above this voltage, there can be no current flow. The principle is thus similar to the situation when the flow from a water hose is regulated by squeezing the hose.

In the simulation on the right, the same voltage ratios are shown. The toggle switch on the left makes it possible to invert the voltage U_{DS} via the transistor. If this becomes negative, a slightly different situation arises: The JFET seems to become conductive in all, regardless of what voltage U_{GS} assumes.

~CLEARFIX~~

Digital Analogue Converter (DAC)

In chapter 3, a digital-to-analog converter was described in [task 3.5.3](#). The R-2R ladder described there allows a pure digital value to be output as an analog voltage as an integrated circuit. In the

simulation on the right a simplified version can be seen. However, the simplified version requires many very precisely tuned resistors. In contrast, the R-2R ladder requires only 2 resistor values and this is easier to manufacture in terms of microsystem technology.

~PAGEBREAK~ ~CLEARFIX~~

Time Domain - Frequency Domain

arbitrary periodic signals

 Fig. 3: Superposition of sinusoidal oscillations

At the previous chapter a sinusoidal input voltage was used for the analysis. How do the filters work Here we want to focus on it again.

In [figure 3](#) it can be seen that a square wave signal can be approximated by several sinusoidal signals. If the amplitudes of these signals are plotted versus frequency, an image of the signal in the frequency domain is obtained. This transformation is done computationally via the [Fourier transform](#) and is treated in detail in advanced subjects such as control engineering, signals and systems and digital signal processing.

For very fast changes, high-frequency components are required.

Already with the [Umkehraddierer](#) it became apparent that a periodic sawtooth signal can be assembled from several sinusoidal voltages.

~CLEARFIX~~~

 Fig. 4: Superposition of sinusoidal oscillations

 Fig. 5: Approximation of any signal

From the sinus

The video [But what is a Fourier series?](#) explains clearly how even vector images can be generated by superimposing sine functions.

From:
<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:
https://first.mexle.te.hs-heilbronn.de/circuit_design/8_further_aspects

Last update: **2021/09/25 05:14**

