

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \color{blue}{U_E(t)} dt + U_{A0}$	insert sine function	$\color{blue}{U_E(t)} = \hat{U}_E \sin(\omega \cdot t)$
$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \color{blue}{\sin(\omega \cdot t)} dt + U_{A0}$	insert root function with \limits	$\int_{t_0}^{t_1} \sin(a \cdot x) dx = [-\frac{1}{a} \cos(a \cdot x)]_{t_0}^{t_1}$
$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$	put constant before \ integral	
$U_A = \frac{1}{\omega \cdot C} \left[\cos(\omega \cdot t) \right]_{t_0}^{t_1} + U_{A0}$	insert limits	$t_0=0, t_1=t$
$U_A = \frac{\hat{U}_E}{\omega \cdot C} \left[\cos(\omega \cdot t) - \cos(0) \right] + U_{A0}$		$\color{blue}{\cos(0)} = 1$
$U_A = \frac{\hat{U}_E}{\omega \cdot C} \left[\cos(\omega \cdot t) - 1 \right] + U_{A0}$	multiply	
$U_A = \frac{\hat{U}_E}{\omega \cdot C} \left[\cos(\omega \cdot t) - 1 \right] + U_{A0}$	consider the \non-cosine terms	
$U_A = \frac{\hat{U}_E}{\omega \cdot C} \left[\cos(\omega \cdot t) - 1 \right] + U_{A0}$	This part is independent in time. Since we assume purely sinusoidal quantities, the for the initial voltage of the capacitor must be:	$U_{C0} = U_{A0} = \frac{\hat{U}_E}{\omega \cdot C}$
$U_A = \frac{\hat{U}_E}{\omega \cdot C} \left[\cos(\omega \cdot t) - 1 \right] + U_{A0}$		
$U_A = \frac{\hat{U}_E}{\omega \cdot C} \left[\cos(\omega \cdot t) - 1 \right] + U_{A0}$		

From: <https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1632540188

Last update: 2021/09/25 05:23

