

# rechnung\_betragundphase\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \color{blue}{U_E(t)} dt + U_{A0}$	insert sine function	$\color{blue}{U_E(t)} = \hat{U}_E \sin(\omega \cdot t)$
$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \color{blue}{\hat{U}_E \sin(\omega \cdot t)} dt + U_{A0}$	insert root function with limits	$\color{blue}{\int_{x_0}^{x_1} \sin(a \cdot x) dx} = [-\frac{1}{a} \cos(a \cdot x)]_{x_0}^{x_1}$
$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \color{blue}{\hat{U}_E \cos(\omega \cdot t)} dt + U_{A0}$	put constant before integral	
$U_A = \frac{1}{\omega R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$	insert limits	$t_0=0, t_1=t$
$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$		$\color{blue}{\cos(0)} = 1$
$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$	multiply	
$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$	consider the non-cosine terms	
$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$	This part is independent in time. Since we assume purely sinusoidal quantities, the for the initial voltage of the capacitor must be: $U_{A0} = \frac{\hat{U}_E}{\omega R \cdot C}$	
$U_A = \frac{\hat{U}_E}{\omega R \cdot C} \int_{t_0}^{t_1} \color{blue}{\cos(\omega \cdot t)} dt + U_{A0}$		

From: <https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: [https://first.mexle.te.hs-heilbronn.de/circuit\\_design/rechnung\\_betragundphase\\_umkehrintegrator?rev=1632676812](https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1632676812)

Last update: 2021/09/26 19:20

