

# rechnung\_betragundphase\_umkehrintegrator

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

\$\;\$ \$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} U_E(t) \, dt + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert sine function: $U_E(t) = \hat{U}_E \cdot \sin(\omega \cdot t)$
\$\;\$ \$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \int_{t_0}^{t_1} \hat{U}_E \cdot \sin(\omega \cdot t) \, dt + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert root function with limits $\int_{x_0}^{x_1} \sin(a \cdot x) \, dx = [-\frac{1}{a} \cdot \cos(a \cdot x)]_{x_0}^{x_1}$
\$\;\$ \$\;\$ \$\;\$	$U_A = -\frac{1}{R \cdot C} \cdot [-\frac{\hat{U}_E}{\omega} \cdot \cos(\omega \cdot t)]_{t_0}^{t_1} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	put constant before integral $U_A = \frac{\hat{U}_E}{\omega \cdot R \cdot C} \cdot \{ \cos(\omega \cdot t) - \cos(0) \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert limits: $t_0=0, t_1=t$ $U_A = \frac{\hat{U}_E}{\omega \cdot R \cdot C} \cdot \{ \cos(\omega \cdot t) - \cos(0) \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega \cdot R \cdot C} \cdot \{ \cos(\omega \cdot t) - 1 \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	multiply $U_A = \frac{\hat{U}_E}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t) \cdot \{ -\frac{\hat{U}_E}{\omega \cdot R \cdot C} \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	consider the non-cosine terms: The blue part is independent in time. We assume purely sinusoidal quantities!
\$\;\$ \$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t) \cdot \{ -\frac{\hat{U}_E}{\omega \cdot R \cdot C} \} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	$U_{C0} = U_{A0} = \frac{\hat{U}_E}{\omega \cdot R \cdot C}$
\$\;\$ \$\;\$ \$\;\$	$U_A = \frac{\hat{U}_E}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t)$
\$\;\$ \$\;\$ \$\;\$	

From:

<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

[https://first.mexle.te.hs-heilbronn.de/circuit\\_design/rechnung\\_betragundphase\\_umkehrintegrator?rev=1641770698](https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1641770698)

Last update: **2022/01/10 00:24**

