

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$\;\$ \$\;\$ \$\;\$	$U_O = -\frac{1}{R \cdot C} \int \int U_I(t) dt + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert sine function: $U_I(t) = \hat{U}_I \cdot \sin(\omega \cdot t)$
\$\;\$ \$\;\$ \$\;\$	$U_O = -\frac{1}{R \cdot C} \int \int \hat{U}_I \cdot \sin(\omega \cdot t) dt + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert root function with limits $\int_{x_0}^{x_1} \sin(a \cdot x) dx = [-\frac{1}{a} \cdot \cos(a \cdot x)]_{x_0}^{x_1}$
\$\;\$ \$\;\$ \$\;\$	$U_O = -\frac{1}{R \cdot C} \cdot [-\frac{\hat{U}_I}{\omega} \cdot \cos(\omega \cdot t)]_{t_0}^{t_1} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	put constant before integral $U_O = \frac{1}{R \cdot C} \cdot \frac{\hat{U}_I}{\omega} \cdot [\cos(\omega \cdot t)]_{t_0}^{t_1} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	insert limits: $t_0=0, t_1=t$ $U_O = \frac{\hat{U}_I}{\omega \cdot R \cdot C} \cdot (\cos(\omega \cdot t) - \cos(0)) + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	$\cos(0) = 1$
\$\;\$ \$\;\$ \$\;\$	$U_O = \frac{\hat{U}_I}{\omega \cdot R \cdot C} \cdot (\cos(\omega \cdot t) - 1) + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	multiply $U_O = \frac{\hat{U}_I}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t) - \frac{\hat{U}_I}{\omega \cdot R \cdot C} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	consider the non-cosine terms: The blue part is independent in time. We assume purely sinusoidal quantities!
\$\;\$ \$\;\$ \$\;\$	$U_O = \frac{\hat{U}_I}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t) - \frac{\hat{U}_I}{\omega \cdot R \cdot C} + U_{A0}$
\$\;\$ \$\;\$ \$\;\$	$U_{C0} = U_{A0} = \frac{\hat{U}_I}{\omega \cdot R \cdot C}$
\$\;\$ \$\;\$ \$\;\$	$U_O = \frac{\hat{U}_I}{\omega \cdot R \cdot C} \cdot \cos(\omega \cdot t)$

From:

<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1675186646

Last update: **2023/01/31 18:37**

