

rechnung_nichtinvertierender_verstaerker_eingangswiderstand

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$R_E^0 = \frac{U_E}{I_p}$		
$R_E^0 = \frac{U_E}{I_p}$		mit I_p aus $R_D = \frac{U_D}{I_p}$
$R_E^0 = \frac{U_E \cdot R_D}{R_D + U_D}$		
$R_E^0 = \frac{U_E \cdot R_D}{R_D + U_D}$		mit $U_D = \frac{U_A}{A_D}$
$R_E^0 = \frac{U_E \cdot R_D}{R_D + U_D}$		umgeformt
$R_E^0 = \frac{U_E}{U_A} \cdot R_D \cdot A_D$		
$R_E^0 = \frac{U_E}{U_A} \cdot R_D \cdot A_D$		mit $A_V = \frac{U_E}{U_A} = \frac{R_2}{R_1 + R_2}$
$R_E^0 = \frac{1}{A_V} \cdot R_D \cdot A_D$		
$R_E^0 = \frac{A_D}{A_V} \cdot R_D$		

From:
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_nichtinvertierender_verstaerker_eingangswiderstand?rev=1632192975

Last update: 2021/09/21 04:56

