

rechnung_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = f(U_E)$
with III.
$U_A = \frac{1}{A_D} \cdot U_E$
with II. and I.: $\frac{1}{A_D} \cdot U_E = \frac{1}{C} \cdot \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$
$U_A = \frac{1}{C} \cdot \int_{t_0}^{t_1} I_C dt + Q_0(t_0)$
with V.: $\frac{1}{C} \cdot \int_{t_0}^{t_1} I_C dt = \frac{1}{C} \cdot \int_{t_0}^{t_1} I_R dt + Q_0(t_0)$
$U_A = \frac{1}{C} \cdot \int_{t_0}^{t_1} I_R dt + Q_0(t_0)$
Factor out
$U_A = -\frac{1}{C} \cdot \int_{t_0}^{t_1} I_R dt - \frac{Q_0(t_0)}{C}$
consider the integration constant: $\frac{Q_0(t_0)}{C} = U_C(t_0) = -U_{A0}$
$U_A = -\frac{1}{C} \cdot \int_{t_0}^{t_1} I_R dt + U_{A0}$
with VI. and II.: $\frac{1}{C} \cdot \int_{t_0}^{t_1} I_R dt = \frac{1}{R} \cdot \int_{t_0}^{t_1} U_E dt + U_{A0}$
move constant ahead
$U_A = -\frac{1}{R \cdot C} \cdot \int_{t_0}^{t_1} U_E dt + U_{A0}$
insert time constant $\tau = R \cdot C$
$U_A = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E dt + U_{A0}$

From:
<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:
https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_umkehrintegrator?rev=1641768985

Last update: **2022/01/09 23:56**

