

rechnung_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

$U_A = f(U_E)$
with III.
$U_A = \frac{1}{A_D} \cdot U_E$
with II. and I.: $\frac{1}{A_D} \cdot U_E = \frac{1}{C} \cdot \int_0^t I_C \, dt + Q_0(t_0)$
$U_A = \frac{1}{C} \cdot \int_0^t I_C \, dt + Q_0(t_0)$
with V.: $\frac{1}{C} \cdot \int_0^t I_C \, dt = \frac{1}{R} \cdot \int_0^t U_E \, dt$
$U_A = \frac{1}{R \cdot C} \cdot \int_0^t U_E \, dt + U_{A0}$
Factor out
$U_A = \frac{1}{R \cdot C} \cdot \int_0^t U_E \, dt + U_{A0}$
consider the integration constant: $U_{A0} = U_C(t_0) = -U_{A0}$
$U_A = \frac{1}{R \cdot C} \cdot \int_0^t U_E \, dt + U_{A0}$
with VI. and II.: $\frac{1}{R} \cdot U_E = \frac{1}{R} \cdot U_E$
$U_A = \frac{1}{R \cdot C} \cdot \int_0^t U_E \, dt + U_{A0}$
move constant ahead
$U_A = \frac{1}{R \cdot C} \cdot \int_0^t U_E \, dt + U_{A0}$
insert time constant $\tau = R \cdot C$
$U_A = \frac{1}{\tau} \cdot \int_0^t U_E \, dt + U_{A0}$

From:
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_umkehrintegrator?rev=1641769035

Last update: 2022/01/09 23:57

