

rechnung_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

	$U_A = f(U_E)$
	with III.
$U_A = \frac{1}{A_D} U_C$	
with II. and I.: $\frac{1}{A_D} U_C = \frac{1}{A_D} U_C \cdot \frac{A_D}{A_D} \rightarrow \infty \rightarrow 0$	
$U_A = 0 - \frac{1}{C} \int_0^1 I_C dt + Q_0(t_0)$	
with V.: $\frac{1}{C} \int_0^1 I_C dt + Q_0(t_0)$	
$U_A = -\frac{1}{C} \int_0^1 I_C dt + Q_0(t_0)$	
with IV.: $I_C = I_R$	
$U_A = -\frac{1}{C} \int_0^1 I_R dt + Q_0(t_0)$	
Factor out	
$U_A = -\frac{1}{C} \int_0^1 I_R dt - \frac{Q_0(t_0)}{C}$	
consider the integration constant: $\frac{Q_0(t_0)}{C} = U_C(t_0) = -U_{A0}$	
$U_A = -\frac{1}{C} \int_0^1 I_R dt + U_{A0}$	
with VI. and II.: $I_R = \frac{U_R}{R} = \frac{U_E}{R}$	
$U_A = -\frac{1}{C} \int_0^1 \frac{U_E}{R} dt + U_{A0}$	
move constant ahead	
$U_A = -\frac{1}{R \cdot C} \int_0^1 U_E dt + U_{A0}$	
insert time constant $\tau = R \cdot C$	
$U_A = -\frac{1}{\tau} \int_0^1 U_E dt + U_{A0}$	

From:

<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://first.mexle.te.hs-heilbronn.de/circuit_design/rechnung_umkehrintegrator?rev=1641769142

Last update: 2022/01/09 23:59

