

task_abh4vhlgczdbni37_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Signal Analysis (written test, approx. 6 % of a 120-minute written test, SS2021)

..... 2

signal analysis, RMS, exam ee2 SS2021

Exercise E1 Signal Analysis**(written test, approx. 6 % of a 120-minute written test, SS2021)**

A) Determine the effective value of the signal $i(t)$ and the effective value of the voltage $u(t)$ (independent quantities are available in the consumer arrow system). (hard)

$$u(t) = 50 \sqrt{2} \cos(6000 \frac{1}{s} t + 4) \text{ V}$$

$$i(t) = 30 \sqrt{2} \sin(6000 \frac{1}{s} t + 5) \text{ A}$$

Result

a) Determine the amplitude values $\hat{U}$, $\hat{I}$ and the RMS values U , I

$$f = 955 \text{ Hz}$$

$$\hat{U} = 50 \sqrt{2} \text{ V}$$

The frequency can be derived by the term in the sine function: $\omega = 6000 \frac{1}{s}$ (inductive) $f = \frac{\omega}{2\pi} = 954.93 \dots \text{ Hz}$

RMS values:

For the phase φ , we have to subtract φ_i from φ_u .

But to get these values, both the $u(t)$ and $i(t)$ need to have the same sinusoidal function! Therefore:

- For the RMS values of sinusoidal functions the amplitudes have to be multiplied with $\frac{1}{\sqrt{2}}$
- $\varphi_u = 4 + \frac{\pi}{2}$

$$\varphi = \varphi_u - \varphi_i = 4 + \frac{\pi}{2} - 5 = 2.14159 \dots$$

$$\text{Converted in degree: } \varphi = 2.14159 \dots \cdot \frac{360^\circ}{2\pi} = 32.7042 \dots^\circ$$

From:

<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://first.mexle.te.hs-heilbronn.de/ee2/task_abh4vhlgczdmbni37_with_calculation

Last update: 2024/07/04 02:36

