

Exam Summer Semester 2023

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E2 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E3 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E4 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	4
Exercise E5 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	5
Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	6
Exercise E7 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	8
Exercise E8 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	12
Exercise E9 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	16
Exercise E10 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	17
Exercise E11 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E12 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E13 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E14 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E15 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written	

test, WS2022)	21
Exercise E16 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	24

Exercise E1 Resistance of a Wire by Resistivity**(written test, approx. 6 % of a 60-minute written test, WS2022)**

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used for electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I needed to operate the heating elements.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ \sqrt{\frac{P}{R}} &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \text{and } R = \\ 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

Exercise E2 Resistance of a Wire by Resistivity**(written test, approx. 6 % of a 60-minute written test, WS2022)**

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used for electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I needed to operate the heating elements.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ \sqrt{\frac{P}{R}} &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \text{and } R = \\ 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

Exercise E3 Temperature-dependent Resistance

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A digital display shows a temperature coefficient of resistance of a thermistor. The thermistor has a resistance of $10 \text{ k}\Omega$ at 25°C . Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

Calculate the resistance of the thermistor at -40°C .

$$R = 10 \text{ k}\Omega \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

The power transfer resistor P is the output of the circuit and generates heat. Therefore, a solution is to use a heat sink to cool the resistor.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad \text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot (1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

Exercise E4 Temperature-dependent Resistance**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A digital display shows a temperature coefficient of resistance of a thermistor. The thermistor has a resistance of $10 \text{ k}\Omega$ at 25°C . Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

Calculate the resistance of the thermistor at -40°C .

$$R = 10 \text{ k}\Omega \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

The power transfer resistor P is the output of the circuit and generates heat. Therefore, a solution is to use a heat sink to cool the resistor.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad \text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot (1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2)$$

Exercise E5 Pure Resistor Network Simplification


(written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall now be closed at 10 o'clock. The equivalent resistance R_{eq} between terminals A and B is to be determined. The switch shall now be open. Calculate the equivalent resistance R_{eq} between terminals A and B.

Solution

$$R_{\text{eq}} = 133.8 \, \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

The switch shall now be open. Calculate the equivalent resistance R_{eq} between terminals A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = (R_2 + R_1 + R_3) \parallel (R_2 + R_4) \parallel (100 \, \Omega + 200 \, \Omega + 200 \, \Omega) \parallel (100 \, \Omega + 100 \, \Omega) \parallel (500 \, \Omega) \parallel (200 \, \Omega)$$

$$R_{eq} = \frac{500 \, \Omega \cdot 200 \, \Omega}{500 \, \Omega + 200 \, \Omega}$$


Exercise E6 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be simplified with $R_1 = 200 \, \Omega$, $R_2 = 100 \, \Omega$, $R_3 = 150 \, \Omega$, $R_4 = 100 \, \Omega$ and the voltage source $U_{SV} = 10 \, \text{V}$.
Result given: $R_{eq} = 132.8 \, \Omega$.

Solution

$$R_{eq} = 132.8 \, \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 || R_3) || (R_4 + R_5)$$

$$R_{\text{eq}} = (100 \, \Omega + 200 \, \Omega || 200 \, \Omega) || (100 \, \Omega + 100 \, \Omega)$$

$$R_{\text{eq}} = (500 \, \Omega) || (200 \, \Omega)$$


$$R_{\text{eq}} = \frac{500 \, \Omega \cdot 200 \, \Omega}{500 \, \Omega + 200 \, \Omega}$$

Exercise E7 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result

$$U_s = U_{AB} = 4.5 \, \text{V}$$


$$R_i = R_{AB} = 6 \, \Omega$$




Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :
$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$
 The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:
$$U_{24}$$

$$U_{24} = U_{23} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} = (U_2 - U_4) \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} = (U_2 - U_4) \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$


with $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \cdot \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \quad R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

Exercise E8 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result


$$U_s = U_{AB} = 4.5\text{V} \quad R_i = R_{AB} = 6\Omega$$



Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :

$$I_{24} = \frac{U_{24}}{R_1 + R_3 + R_5} = \frac{(U_1 - U_4) \cdot R_1}{R_1 + R_3 + R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 + R_3 + R_5} = (U_1 - U_4) \cdot \frac{R_7 \cdot R_1}{R_6 + R_7 + R_1 + R_3 + R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 + R_3 + R_5)$$

with $R_1 + R_3 + R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \cdot \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \parallel R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

Exercise E9 Charging Capacitors


(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit below is a simplified model of a battery with an internal resistance R_1 and a capacitor C connected in parallel with a switch S_1 . The voltage across the capacitor is again 0V at the moment $t_0=0\text{s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1\text{ms}$ after closing the switch.


Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

$$U_{\text{eq}} = \frac{U \cdot R_2}{R_1 + R_2} = \frac{12\text{V} \cdot 2\Omega}{1\Omega + 2\Omega} = 8\text{V}$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U=12\text{ V}$, a switch S_1 , a resistor of $R_1=20\text{ }\Omega$ and a capacitor of $C=100\text{ }\mu\text{F}$. The switch S_2 to an additional consumer R_2 will be considered to be open for the first task. At the moment $t_0=0\text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0\text{ V}$.



First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_c(t_1)=0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$. An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($=0\text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1\text{ ms}/(10\text{ }\Omega \cdot 100\text{ }\mu\text{F})})$$

Exercise E10 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (see the solution) consists of a 12 V voltage source, a $20\text{ }\Omega$ resistor, a $100\text{ }\mu\text{F}$ capacitor, and a $20\text{ }\Omega$ resistor. The voltage across the capacitor is again 0 V at the moment $t_0=0\text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1\text{ ms}$ after closing the switch.

Solution


To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .

$$U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U = 6\text{ V}$$

Solution

The ideal voltage source is given by $U_s = U \cdot \frac{R_1}{R_1 + R_B}$ and the internal resistance is given by $R_i = R_1 \parallel R_B$.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ }\Omega$ and a capacitor of $C = 100 \text{ }\mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.



Solution

An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \text{ }\Omega$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$: $u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$. It has to be rearranged to t : $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = -\tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$

Exercise E11 Analyzing complex Impedances

(written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phase angle of the solution $\underline{U} = 50 \angle 0^\circ$ mV and $\underline{Z} = 0.24 - j4.68 \Omega$ in both the components. (φ and $\underline{X}_L$) shall be given.

After analysis, the full bridge dimensioned circuit impedance can be extracted and the phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

... Calculate the physical values of the two components.

Solution $\begin{aligned} R &= 0.24 \Omega \\ X_L &= 4.68 \Omega \end{aligned}$

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{0.24 - j4.68} = 10.4 \angle 87.9^\circ$ A

The current and voltage are in phase since the impedance is purely real (the imaginary part is zero).

resulting impedance $\underline{Z} = 0.24 - j4.68 \Omega$

Therefore, the component 4.68Ω is a capacitor with the same absolute value of 4.68Ω but with a negative sign.

impedance $\underline{Z} = 0.24 - j4.68 \Omega$

$\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

$\varphi = -10.9^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

With the complex part (imaginary part) $\varphi = -10.9^\circ$

$\varphi = -10.9^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

Exercise E12 Analyzing complex Impedances

(written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the phase angle of the solution $\underline{U} = 50 \angle 0^\circ$ mV and $\underline{Z} = 0.24 - j4.68 \Omega$ in both the components. (φ and $\underline{X}_L$) shall be given.

After analysis, the full bridge dimensioned circuit impedance can be extracted and the phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

... Calculate the physical values of the two components.

Solution $\begin{aligned} R &= 0.24 \Omega \\ X_L &= 4.68 \Omega \end{aligned}$

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{0.24 - j4.68} = 10.4 \angle 87.9^\circ$ A

The current and voltage are in phase since the impedance is purely real (the imaginary part is zero).

resulting impedance $\underline{Z} = 0.24 - j4.68 \Omega$

Therefore, the component 4.68Ω is a capacitor with the same absolute value of 4.68Ω but with a negative sign.

impedance $\underline{Z} = 0.24 - j4.68 \Omega$

$\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

$\varphi = -10.9^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -10.9^\circ$

The absolute value of the impedance is $Z = \sqrt{(0.24 \sim \Omega)^2 + (4.68 \sim \Omega)^2} = 4.7 \sim \Omega$
 $\varphi = \arctan\left(\frac{4.68 \sim \Omega}{0.24 \sim \Omega}\right) = 87.1^\circ$
 With the complex part comes the physical value: $X_L = \omega L = 2\pi \cdot 4.7 \sim \Omega$
 The phase $\varphi = 87.1^\circ$ is the angle between the voltage and the current. $\varphi = 87.1^\circ$
 $\varphi = \arctan\left(\frac{4.68 \sim \Omega}{0.24 \sim \Omega}\right) = 87.1^\circ$

Exercise E13 Impedances at different Frequencies

(written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$
 Parallel circuit means that the voltage is the same on R_3 and C_3
 $\frac{1}{Z} = \frac{1}{R_3} + \frac{1}{X_{C3}}$
 Back to the first formula: $R_3 \cdot I_{3R} = X_{C3} \cdot I_{3C}$
 $I_{3R} = \frac{U_{3R}}{R_3} = \frac{U_{3C}}{X_{C3}} = \frac{U_{3C}}{\frac{1}{\omega C_3}} = U_{3C} \cdot \omega C_3$
 $U_{3R} = I_{3R} \cdot R_3 = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

Solution

$R_1 = 1.00 \sim \Omega$

$R_2 = 10.0 \sim \Omega$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$

Parallel circuit means that the voltage is the same on R_3 and C_3
 $\frac{1}{Z} = \frac{1}{R_3} + \frac{1}{X_{C3}}$
 Back to the first formula: $R_3 \cdot I_{3R} = X_{C3} \cdot I_{3C}$
 $I_{3R} = \frac{U_{3R}}{R_3} = \frac{U_{3C}}{X_{C3}} = \frac{U_{3C}}{\frac{1}{\omega C_3}} = U_{3C} \cdot \omega C_3$
 $U_{3R} = I_{3R} \cdot R_3 = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

$U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

Therefore, the resulting current of the parallel circuit is given as: $I = \frac{U}{Z}$

$I = \frac{U}{Z} = \frac{U}{\sqrt{R^2 + X_L^2}}$

This can be simplified to: $I = \frac{U}{\sqrt{R^2 + X_L^2}}$
 $I = \frac{U}{\sqrt{R^2 + X_L^2}}$
 $I = \frac{U}{\sqrt{R^2 + X_L^2}}$

Back to the first formula: $R_3 \cdot I_{3R} = X_{C3} \cdot I_{3C}$
 $I_{3R} = \frac{U_{3R}}{R_3} = \frac{U_{3C}}{X_{C3}} = \frac{U_{3C}}{\frac{1}{\omega C_3}} = U_{3C} \cdot \omega C_3$
 $U_{3R} = I_{3R} \cdot R_3 = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

Back to the first formula: $R_3 \cdot I_{3R} = X_{C3} \cdot I_{3C}$
 $I_{3R} = \frac{U_{3R}}{R_3} = \frac{U_{3C}}{X_{C3}} = \frac{U_{3C}}{\frac{1}{\omega C_3}} = U_{3C} \cdot \omega C_3$
 $U_{3R} = I_{3R} \cdot R_3 = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

$U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

$U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

$U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$
 $U_{3R} = U_{3C} \cdot \omega C_3 \cdot R_3$

Exercise E14 Impedances at different Frequencies

(written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E14 The resistor values $2347 \sim \Omega$ and $10 \sim \Omega$ are in the AC voltage source of $35 \sim V$. R_1 and R_2 are in series, and R_3 is in parallel with the series combination of R_1 and R_2 . The voltage source is $u(t) = 35 \sim V \cdot \sin(2\pi \cdot 10^3 \cdot t)$. The resistor R_1 shall have the same absolute value of the impedance as a capacitor $C_1 = 40 \sim nF$ at $f = 4 \sim MHz$.

Solution:

$$R_1 = 1.00 \sim \Omega$$

$$R_2 = 10.0 \sim \Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by
$$Z_{RL} = R + j\omega L$$
 Parallel circuit means that the voltage is the same on R_1 and R_2
$$U = U_{R1} = U_{R2}$$
 Since $U_{R1} = U_{R2}$ and $I_{R1} = I_{R2}$ (series circuit)
$$R_1 = R_2$$
 The voltage across R_3 is $U_{R3} = U - U_{RL}$ The current through R_3 is $I_{R3} = \frac{U_{R3}}{R_3}$ The current through R_1 and R_2 is $I_{R1} = I_{R2} = \frac{U_{R1}}{R_1}$ The total current is $I = I_{R1} + I_{R2} + I_{R3}$ The voltage across R_1 and R_2 is $U_{R1} = U_{R2} = U \cdot \frac{R_1}{R_1 + R_2 + R_3}$ The voltage across R_3 is $U_{R3} = U \cdot \frac{R_3}{R_1 + R_2 + R_3}$ The current through R_3 is $I_{R3} = \frac{U_{R3}}{R_3} = \frac{U}{R_1 + R_2 + R_3}$ The current through R_1 and R_2 is $I_{R1} = I_{R2} = \frac{U_{R1}}{R_1} = \frac{U}{R_1 + R_2 + R_3}$ The total current is $I = I_{R1} + I_{R2} + I_{R3} = \frac{U}{R_1 + R_2 + R_3}$ The voltage across R_1 and R_2 is $U_{R1} = U_{R2} = U \cdot \frac{R_1}{R_1 + R_2 + R_3}$ The voltage across R_3 is $U_{R3} = U \cdot \frac{R_3}{R_1 + R_2 + R_3}$ The current through R_3 is $I_{R3} = \frac{U_{R3}}{R_3} = \frac{U}{R_1 + R_2 + R_3}$ The current through R_1 and R_2 is $I_{R1} = I_{R2} = \frac{U_{R1}}{R_1} = \frac{U}{R_1 + R_2 + R_3}$ The total current is $I = I_{R1} + I_{R2} + I_{R3} = \frac{U}{R_1 + R_2 + R_3}$

Exercise E15 Complex Impedance Circuit

(written test, approx. 15 % of a 60-minute written test, WS2022)

Exercise E15 Calculate the complex impedance Z for the circuit shown. The voltage source is $u(t) = 3.0 \sim V \cdot \sin(2\pi \cdot 15 \sim kHz \cdot t)$. The resistor R_1 shall have the same absolute value of the impedance as a capacitor $C_1 = 40 \sim nF$ at $f = 4 \sim MHz$.

Solution:
 The linear source is connected with an inductor of $330 \sim \mu H$ and a capacitor of $0.22 \sim \mu F$, all in series.

Result:

$$Z = 48.2 \sim \Omega$$

$$Z_C = \frac{1}{j\omega C} = \frac{1}{j \cdot 2\pi \cdot 15 \cdot 10^3 \cdot 0.22 \cdot 10^{-6}} = -j48.2 \sim \Omega$$

$$Z_L = j\omega L = j \cdot 2\pi \cdot 15 \cdot 10^3 \cdot 330 \cdot 10^{-6} = j31.6 \sim \Omega$$


$$Z = Z_L + Z_C = j31.6 - j48.2 = -j16.6 \sim \Omega$$


$$|Z| = 16.6 \sim \Omega$$

$$\angle Z = -90^\circ$$

$$Z = 16.6 \sim \Omega \cdot e^{-j90^\circ} = -j16.6 \sim \Omega$$







From:

<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/ss2023_exam?rev=1690213984

Last update: **2023/07/24 17:53**

