

# task\_70jg4yzznocarsq\_with\_calculation

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

temperature dependent resistance, power, heat, exam ee1 WS2022

## Exercise 1.1 : Temperature-dependent Resistance

(written test, approx. 6% of a 60-minute written test, WS2022)

A thermistor is used as a temperature sensor in a refrigeration system. The thermistor has a resistance of  $10 \text{ k}\Omega$  at  $+25 \text{ }^\circ\text{C}$ .

Its temperature coefficients are:  $\alpha = 0.01 \frac{1}{\text{K}}$  and  $\beta = 71 \cdot 10^{-6} \frac{1}{\text{K}^2}$

The temperature inside the refrigeration system can reach down to  $-40 \text{ }^\circ\text{C}$ .

1. Calculate the resistance of the thermistor at  $-40 \text{ }^\circ\text{C}$ .

Solution

$$\begin{aligned} R &= R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \\ \text{with } \Delta T &= T_{\text{end}} - T_{\text{start}} \quad | \quad R = 10 \text{ k}\Omega \cdot \left(1 + \right. \\ &0.01 \frac{1}{\text{K}} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C}) + 71 \cdot \\ &10^{-6} \frac{1}{\text{K}^2} \cdot (-40 \text{ }^\circ\text{C} - 25 \text{ }^\circ\text{C})^2 \left. \right) \end{aligned}$$

Final result

$$R = 6.5 \text{ k}\Omega$$

2. Additionally, explain which effect a resistive temperature sensor can have on the refrigeration system.

Solution

Resistors transfer electrical energy out of the circuit and generate heat. Therefore, a resistive sensor might heat up the refrigeration system.

3. Regarding question 2.: Given a constant sensor voltage, would a sensor with tenfold the resistance be better or worse? Give an explanation for your answer.

Solution

The power of the resistor  $P = U \cdot I = R \cdot I^2 = \frac{U^2}{R}$  is equivalent with the heat flow.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one tenth.

From:

<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

[https://first.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/task\\_70jig4yzznocarsq\\_with\\_calculation?rev=1678465017](https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_70jig4yzznocarsq_with_calculation?rev=1678465017)

Last update: **2023/03/10 17:16**

