

task_70jjg4yzznocarsq_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1.1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute
written test, WS2022) 2

temperature dependent resistance, power, heat, exam ee1 WS2022

Exercise E1.1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

A thermistor, which exhibits a linear effect, is sensitive to temperature variations. The thermistor has a resistance of $10 \text{ k}\Omega$ at 25°C . Its temperature coefficients are: $\alpha = 0.01 \text{ }^\circ\text{C}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ }^\circ\text{C}^{-2}$.

Result
The temperature inside the refrigeration system can reach down to -40°C .

1. Calculate the resistance of the thermistor at -40°C .

$$R = 6.5 \text{ k}\Omega$$

The power transfer resistor P is given by $P = \frac{U^2}{R}$ and $Q = P \cdot t$. Therefore, a solution is to increase the heat flow up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot \left(1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2\right)$$

From:
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_70jig4yzznocarsq_with_calculation?rev=1680123524

Last update: 2023/03/29 22:58

