task_rj0r6j4apumukrj6_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

resistivity, power, exam ee1 WS2022

Exercise 1.1 : Resistance of a Wire by Resistivity

(written test, approx. 6% of a 60-minute written test, WS2022)

A heating element made of a Nichrome wire with a round cross-section is used in an electric oven.
Nichrome is a common Nickel Chromium alloy for heating elements.
The Nichrome wire has a resistivity of $1.10\cdot 10^{-6} ~\Omega \rm{m}$.
The heating element is $3 ~\rm{m}$ long and has a diameter of $3.57 ~\rm{mm}$.

1. Calculate the resistance R of the heating element.

Solution

$$\begin{align*} R &= \rho \cdot \frac{l}{A} && \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \\ R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} && \\ R &= 1.10\cdot 10^{-6} ~\Omega \rm{m} \cdot \frac{4 \cdot 3~\rm{m}}{(3.57\cdot 10^{-3}~\rm{m})^2 \cdot \pi} && \\ \end{align*}$$

Final result

$$\begin{align*} R &= 0.33 ~\Omega \\ \end{align*}$$

2. The heating element is used to heat the oven to a temperature of $180~°\rm{C}$. For this, a power dissipation (= heat flow) of $P=40 ~\rm{W}$ is necessary.
Calculate the current I needed to operate it.

Solution

$$\begin{align*} P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I= \sqrt{\frac{P}{R}} = \sqrt{\frac{40 ~\rm{W}}{0.33 ~\Omega}} \end{align*}$$

Final result

$$\begin{align*} I = 11 ~\rm{A} \end{align*}$$

From:
https://first.mexle.te.hs-heilbronn.de/ - **MEXLE Wiki**

Permanent link:
https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_rj0r6j4apumukrj6_with_calculation?rev=1678465510

Last update: **2023/03/10 17:25**