

task_rj0r6j4apumukrj6_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1.1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute
written test, WS2022) 2

resistivity, power, exam ee1 WS2022

include_n1_100

Exercise E1.1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

2. Heating elements are used to heat wire with a temperature of 180°C . Electric power dissipation (= heat flow) of $P=40\text{ W}$ is necessary. Calculate the current I needed to operate it.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6}\text{ }\Omega\text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

Solution: $R = 10^{-3}\text{ }\Omega$

1. Calculate the resistance R of the heating element.

Solution: $P = U \cdot I = R \cdot I^2 \Rightarrow I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40\text{ W}}{0.33\text{ }\Omega}} = 10.98\text{ A}$

$R = \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad || \quad R = \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} = \frac{4 \cdot \rho \cdot l}{\pi d^2} = \frac{4 \cdot 1.10 \cdot 10^{-6}\text{ }\Omega\text{ m} \cdot 3\text{ m}}{\pi (3.57 \cdot 10^{-3}\text{ m})^2} = 10^{-3}\text{ }\Omega$

From: <https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_rj0r6j4apumukrj6_with_calculation?rev=1680241925

Last update: 2023/03/31 07:52

