

task_tb6pi8dgh0m2e2pw_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,
WS2022) 2

Charging Capacitors, dc network analysis, pure resistor network simplification, delta wye transformation, exam ee1 WS2022

Exercise E1 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (without the calculation) also takes into account the charging of a capacitor. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.


Solution
To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .

$$U_{\text{eq}} = U \cdot \frac{R_B}{R_1 + R_B} = 12 \text{ V} \cdot \frac{20 \text{ } \Omega}{20 \text{ } \Omega + 20 \text{ } \Omega} = 6 \text{ V}$$

Solution
The internal resistance is given by substituting the ideal voltage source is again short-circuiting R_1 .

$$R_{\text{eq}} = R_1 \parallel R_B = 20 \text{ } \Omega \parallel 20 \text{ } \Omega = 10 \text{ } \Omega$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_1 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ } \Omega$ and a capacitor of $C = 100 \text{ } \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = 1/2 \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($= 0 \text{ } \Omega$, short-circuit).

So if we only R_1 and C give us the time constant $\tau = R_1 \cdot C$ and $\omega = \frac{1}{\tau}$

The following formula describes the time course $u_c(t)$ which has $\{1 \text{ V}\}$ $u_c(t) = 0.5 \cdot (1 - e^{-\frac{t}{\tau}})$ $(10 - (10 - 0.5) \cdot e^{-\frac{t}{\tau}})$ 0.5 and $\tau = R_1 \cdot C$ It has to be rearranged to $(1 - e^{-\frac{t}{\tau}}) = 0.5$ $e^{-\frac{t}{\tau}} = 0.5$ $\frac{t}{\tau} = \ln(0.5)$ $t = \tau \cdot \ln(0.5)$ $t = R_1 \cdot C \cdot \ln(0.5)$

From:
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_tb6pi8dgh0m2e2pw_with_calculation?rev=1680388533

Last update: 2023/04/02 00:35

