

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023) ..... 2

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 3

Exercise E2 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023) ..... 3

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 4

**Exercise E1 Resistivity and temperature dependent Resistance  
(written test, approx. 7 % of a 60-minute written test, SS2023)**

The conductivity of a dielectric material is described by the Arrhenius law:  $\rho = \rho_0 \cdot \exp(-E_a / (k_B \cdot T))$ . The activation energy  $E_a$  is given as  $0.8 \text{ eV}$ . The pre-exponential factor  $\rho_0$  is given as  $10^{17} \text{ } \Omega^{-1} \text{ m}^{-1}$ . The temperature  $T$  is given as  $20 \text{ } ^\circ\text{C}$  and  $55 \text{ } ^\circ\text{C}$ .

**Solution**  
The resistivity of the dielectric material is  $\rho_{PP}(20 \text{ } ^\circ\text{C}) = 10^{17} \text{ } \Omega \text{ m}$ .

For the given material the temperature coefficients in the range  $20 \text{ } ^\circ\text{C}$  and  $55 \text{ } ^\circ\text{C}$

are given as  $\alpha = -0.048 \text{ } ^\circ\text{C}^{-1}$  and  $\beta = +0.00057 \text{ } ^\circ\text{C}^{-2}$ .

$$\begin{aligned} R(55 \text{ } ^\circ\text{C}) &= R(20 \text{ } ^\circ\text{C}) \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2 + \dots) \\ &= 80 \text{ } \Omega \cdot (1 - 0.048 \text{ } ^\circ\text{C}^{-1} \cdot (35 \text{ } ^\circ\text{C}) + 0.00057 \text{ } ^\circ\text{C}^{-2} \cdot (35 \text{ } ^\circ\text{C})^2) \end{aligned}$$

Calculate the resistance for the dielectric material for  $20 \text{ } ^\circ\text{C}$ .

Solution

$$R(20 \text{ } ^\circ\text{C}) = \rho \cdot \frac{d}{A} = 10^{17} \text{ } \Omega \text{ m}$$

$$I = \frac{0.8 \cdot 10^{-6} \cdot V}{1 \cdot 10^{-2}} \quad \text{align*}$$

resistivity, power, exam ee1 ss2023

**Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)**

A heating element made of nichrome wire with a temperature coefficient of \$1.80 \cdot 10^{-5} \text{ K}^{-1}\$ is used. The electric power dissipation (= heat flow) of \$P=40 \text{ W}\$ is necessary. Calculate the current \$I\$ and the operating voltage \$U\$ for heating elements. The Nichrome wire has a resistivity of \$1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}\$.

The heating element is \$3 \text{ m}\$ long and has a diameter of \$3.57 \text{ mm}\$.  
 Solution:  $R = 10^{-3} \text{ } \Omega$   
 .. Calculate the resistance \$R\$ of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \quad \text{align*}$$

$$R = \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad \parallel \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \parallel \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad \text{align*}$$

resistivity, power, exam ee1 ws2022

**Exercise E2 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)**

The conductivity \$\sigma\$ of a dielectric material is described by the Arrhenius law: \$\sigma = \sigma\_0 \cdot \exp(-E\_a / (k\_B \cdot T))\$. The activation energy \$E\_a\$ is \$0.8 \text{ eV}\$ and the pre-exponential factor \$\sigma\_0\$ is \$10^{17} \text{ } \Omega^{-1} \cdot \text{m}^{-1} \cdot \text{s}^{-1}\$ for \$T = 20 \text{ } ^\circ\text{C}\$ and \$100 \text{ } ^\circ\text{C}\$.

Solution  
 The resistivity of the dielectric material is \$\rho(T) = 10^{17} \text{ } \Omega \cdot \text{m}\$.  
 For the given material the temperature coefficients in the range \$20 \text{ } ^\circ\text{C}\$ and \$55 \text{ } ^\circ\text{C}\$ are given as \$\alpha = -0.048 \text{ } \text{K}^{-1}\$ and \$\beta = +0.00057 \text{ } \text{K}^{-2}\$.

$$R(55 \text{ } ^\circ\text{C}) = R(20 \text{ } ^\circ\text{C}) \cdot (1 + \alpha \cdot \Delta T + \beta \cdot T^2 + \dots) = 80 \text{ } \Omega \cdot (1 - 0.048 \text{ } \text{K}^{-1} \cdot (35 \text{ } \text{K}) + 0.00057 \text{ } \text{K}^{-2} \cdot (35 \text{ } \text{K})^2) \quad \text{align*}$$

Calculate the resistance for the dielectric material for  $20 \text{ }^\circ\text{C}$ .

Solution

$$R(20 \text{ }^\circ\text{C}) = \rho \cdot \frac{d}{A} = 10^{17} \frac{\Omega \cdot \text{m} \cdot 0.8 \cdot 10^{-6} \text{ m}}{1 \text{ m}^2}$$

[resistivity, power, exam ee1 ss2023](#)

**Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)**

**Result**

A minimum power dissipation (= heat flow) of  $P=40 \text{ W}$  is necessary.  
 Calculate the minimum resistance  $R$  of the heating element.  
 The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$ .  
 The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .  
 1. Calculate the resistance  $R$  of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}}$$

$$R = \rho \cdot \frac{l}{A} \quad | \quad A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \quad || \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad || \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi}$$

resistivity, power, exam ee1 ws2022

From:  
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:  
[https://first.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/ws2022\\_exam?rev=1676152918](https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1676152918)

Last update: **2023/02/11 23:01**

