

# Exam Winter Semester 2022

## Student Group

First Name	Surname	Matrikel Nr.

## Table of Contents

- Exercise E5 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 3
- Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 6
- Exercise E9 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 7
- Exercise E13 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 7
- Exercise E11 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 10
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 10
- Exercise E7 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022) ..... 11
- Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) ..... 12
- Exercise E6 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 14
- Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 18
- Exercise E10 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022) ..... 19
- Exercise E14 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022) ..... 19
- Exercise E12 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022) ..... 22
- Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022) ..... 22
- Exercise E8 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,

---


WS2022) .....	23
Exercise E4 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022) .....	24

1

**Exercise E5 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result


$$\begin{aligned} U_{\text{rs}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} \\ &= 6 \text{ } \Omega \end{aligned}$$




Calculated the internal resistance  $R_{\text{i}}$  and the source voltage  $U_{\text{rs}}$  of an equivalent linear voltage source on the connectors  $\text{A}$  and  $\text{B}$ .  
 $R_1=5.0 \text{ } \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3= 10 \text{ } \Omega$ ,  $I_4=4.2 \text{ A}$ ,  
 $R_5=10 \text{ } \Omega$ ,  $R_6=7.5 \text{ } \Omega$ ,  $R_7=15 \text{ } \Omega$  Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ : 
$$R_{135} = R_1 || R_3 || R_5$$
 
$$I_{24} = I_2 - I_4$$
 The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following: 
$$U_{24} = I_{24} \cdot (R_6 || R_7)$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot (R_1 || R_3 || R_5)$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \text{ A} \cdot (15 \Omega \cdot 2.5 \Omega / (7.5 \Omega + 15 \Omega + 2.5 \Omega))$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator is explained with the effect of resistance on the refrigeration system. The circuit has a resistance of  $10 \Omega$  at  $25^\circ \text{C}$  and  $2.5 \Omega$  at  $0^\circ \text{C}$ . Your answer.

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$

**Result**  
The temperature inside the refrigeration system can reach down to  $-40^\circ \text{C}$ .

$$R_{25} = 10 \Omega$$

The power transfer is  $P = U \cdot I = U^2 / R$ . Therefore, a solution is to increase the heat flow up the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \implies R = 10 \Omega \cdot \left( 1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ \text{C} - 25^\circ \text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ \text{C} - 25^\circ \text{C})^2 \right)$$

**Exercise E9 Analyzing complex Impedances**  
 (written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex power  $\underline{S}$  and the real power  $P$  in the circuit shown through the components.  $\underline{U}$  and  $\underline{X}_L$  shall be given.

After analysis, the full complex power  $\underline{S}$  can be calculated as  $\underline{S} = \underline{U} \cdot \underline{I}^*$  in phasor notation.  $\underline{I} = \underline{U} / \underline{Z}$  and  $\underline{Z} = R + j\omega L + 1/(j\omega C)$ .

Solution  
 .. Calculate the physical values of the two components.  
 Solution  $R = 10 \Omega$  and  $L = 20 \text{ mH}$  and  $C = 100 \text{ nF}$

Solution  

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \text{ V}}{10 \Omega + j\omega L + 1/(j\omega C)}$$
 The voltage  $\underline{U} = 50 \text{ V}$  is the reference phasor.  $\omega = 2\pi \cdot 100 \text{ Hz} = 628.3 \text{ rad/s}$   
 resulting impedance  $\underline{Z} = 10 \Omega + j\omega L + 1/(j\omega C) = 10 \Omega + j12.57 \Omega - j15.92 \Omega = 10 \Omega - j3.35 \Omega$   
 Therefore, the component  $L$  is in series with the capacitor  $C$ .  

$$\underline{I} = \frac{50 \text{ V}}{10 \Omega - j3.35 \Omega} = \frac{50 \text{ V}}{10.68 \Omega \angle -17.8^\circ} = 4.68 \text{ A} \angle 17.8^\circ$$

$$\underline{S} = \underline{U} \cdot \underline{I}^* = 50 \text{ V} \cdot 4.68 \text{ A} \angle -17.8^\circ = 234 \text{ VA} \angle -17.8^\circ$$

$$\underline{S} = P + jQ = 220 \text{ W} - j14.7 \text{ var}$$
 The real power  $P = 220 \text{ W}$  and the reactive power  $Q = -14.7 \text{ var}$ .  
 With the complex part  $\varphi = \arctan(Q/P) = \arctan(-14.7/220) = -3.8^\circ$   

$$\varphi = \arctan\left(\frac{\text{Im}(\underline{S})}{\text{Re}(\underline{S})}\right) = \arctan\left(\frac{-14.7}{220}\right) = -3.8^\circ$$

**Exercise E13 Complex Impedance Circuit**  
 (written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the circuit impedance  $\underline{Z}$  for a source  $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$  and  $\underline{Z}$  is the equivalent circuit  $\underline{Z} = R + j\omega L + 1/(j\omega C)$ .

Solution  
 .. Draw the circuit diagram of the given circuit.

Result  

$$\underline{Z} = 10 \Omega + j\omega L + 1/(j\omega C) = 10 \Omega + j15.9 \Omega - j15.9 \Omega = 10 \Omega$$


$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{3.0 \text{ V}}{10 \Omega} = 0.3 \text{ A}$$

$$\underline{S} = \underline{U} \cdot \underline{I}^* = 3.0 \text{ V} \cdot 0.3 \text{ A} = 0.9 \text{ W}$$

$$\underline{S} = P + jQ = 0.9 \text{ W} + j0 \text{ var}$$

$$\varphi = \arctan(Q/P) = \arctan(0/0.9) = 0^\circ$$





**Exercise E11 Impedances at different Frequencies**  
 (written test, approx. 18 % of a 60-minute written test, WS2022)

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$ , a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ , and an inductor with an inductance of  $L_1 = 4.7 \text{ }\mu\text{H}$ . The circuit is connected to an AC voltage source with a voltage of  $U = 10 \text{ V}$  and a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance  $|Z|$  of the circuit.

Solution

$$R_1 = 1.00 \text{ k}\Omega$$

$$R_2 = 10.0 \text{ }\Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for  $R_1$  and  $R_2$  combined is given by 
$$R_{\text{parallel}} = R_1 + R_2$$

Parallel circuit means that the voltage is the same on  $R_1$  and  $R_2$  
$$U = U_{R_1} = U_{R_2}$$

Since  $U_{R_1} = U_{R_2}$  and  $I_{R_1} = I_{R_2}$  (series circuit), we can simplify to 
$$R_1 = R_2$$

$$|Z| = \sqrt{R_{\text{parallel}}^2 + (X_L - X_C)^2}$$

Therefore, the resulting current of the parallel circuit is given as: 
$$I_{\text{parallel}} = \frac{U}{|Z|}$$

Back to the first formula: 
$$R_3 \cdot I_{\text{parallel}} = X_{\text{parallel}} \cdot I_{\text{parallel}}$$

**Exercise E1 Resistance of a Wire by Resistivity**  
 (written test, approx. 6 % of a 60-minute written test, WS2022)

2. Heating elements are used to heat the oven with a temperature of  $180 \text{ }^\circ\text{C}$ . The electric power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary. Calculate the current  $I$  needed to operate the heating elements.

The Nichrome wire has a resistivity of  $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$ .

The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .

Solution

Calculate the resistance  $R$  of the heating element.

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E7 Charging Capacitors**  
 (written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) is a series of  $R_1$  and  $R_2$  and a capacitor  $C$  and a switch  $S_1$  and a switch  $S_2$ . The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution**  
 Hint: To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_2$ .

**Solution**  
 The ideal voltage source  $U$  is in series with  $R_1$  and  $R_2$ . The voltage  $u_c$  is independent of this series combination.


On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_1$ .



The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \Omega$  and a capacitor of  $C = 100 \mu\text{F}$ . The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

**Solution**



An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R = 0 \Omega$ , short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t_1) = 0.5 \cdot U$ :  

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5)$



**Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be solved at 0°C.  $R_1 = R_2 = R_3 = 1.5 \Omega$  and the voltage  $U = 10 \text{ V}$ .  
 Result:  $R_{eq} = 132.8 \Omega$ .

Solution

$$R_{eq} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_{-1}) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \Omega + 200 \Omega + 200 \Omega) \parallel (100 \Omega + 100 \Omega) \parallel R_{\text{eq}} = (500 \Omega) \parallel (200 \Omega) \parallel R_{\text{eq}} = \frac{500 \Omega \cdot 200 \Omega}{500 \Omega + 200 \Omega} \parallel R_{\text{eq}}$$

**Exercise E6 Equivalent linear Source  
(written test, approx. 14 % of a 60-minute written test, WS2022)**

The circuit in the following has to be simplified.  
Result


$$U_{\text{s}} = U_{\text{AB}} = 4.5 \text{ V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \Omega$$




Calculate the internal resistance  $R_{int}$  and the source voltage  $U_{s}$  of an equivalent linear voltage source on the connectors  $A$  and  $B$ .  $R_1=5.0 \Omega$ ,  $U_2=6.0 \text{ V}$ ,  $R_3=10 \Omega$ ,  $I_4=4.2 \text{ A}$ ,  $R_5=10 \Omega$ ,  $R_6=7.5 \Omega$ ,  $R_7=15 \Omega$ . Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of  $U_2$  and  $R_1$  can be transformed into a current source  $I_2 = \frac{U_2}{R_1}$  and  $R_1$ :



Now a lot of them can be combined. The resistors  $R_1$ ,  $R_3$ ,  $R_5$  are in parallel, like also  $I_2$  and  $I_4$ :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the  $U_{24}$  is calculated by  $I_{24}$  as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - I_4 \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by  $R_{135}$ ,  $R_6$ , and  $R_7$ .

Therefore the voltage between  $A$  and  $B$  is given as:

$$U_{AB} = U_{24} \cdot \left( \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \right) - \left( \frac{U_2}{R_1} - I_4 \right) \cdot R_1 || R_3 || R_5$$

For the internal resistance  $R_i$  the ideal voltage source is substituted by its resistance ( $=0 \Omega$ , so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$

with  $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$ :

$$U_{AB} = \left( \frac{6.0 \text{ V}}{5.0 \Omega} \right) - 4.2 \Omega \cdot \left( \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \right)$$

$$R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

**Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator is explained with the effect of resistance on power. The refrigerator has a resistance of  $10 \Omega$  at  $25^\circ \text{C}$  and  $25 \text{ W}$  at  $0^\circ \text{C}$ .

Its temperature coefficients are:  $\alpha = 0.01 \text{ K}^{-1}$  and  $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$ .

**Result** The temperature inside the refrigeration system can reach down to  $-40^\circ \text{C}$ .

Calculate the resistance of the thermistor at  $-40^\circ \text{C}$ .

$$R = 6.5 \text{ k}\Omega$$

The power of the resistor is  $P = U \cdot I$  and  $U = I \cdot R$ . Therefore, a solution is to let the heat flow up the refrigeration system.

Therefore, with constant  $U$  and increasing  $R$  the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2)$$

$$\Delta T = T_{\text{end}} - T_{\text{start}}$$

$$R = 10 \text{ k}\Omega \cdot \left( 1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ \text{C} - 25^\circ \text{C}) + 71 \cdot 10^{-6} \text{ K}^{-2} \cdot (-40^\circ \text{C} - 25^\circ \text{C})^2 \right)$$

### Exercise E10 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)

1. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following dimensions must be provided:  $Z$  in  $\Omega$ ,  $\varphi$  in degrees. The phase shift  $\varphi$  is defined as  $\varphi = \varphi_u - \varphi_i$ .

Solution  
.. Calculate the physical values of the two components.  
Solution  $R = 10 \Omega$  and  $X_L = 2\pi \cdot 15 \cdot 0.2 = 1.88 \Omega$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \quad \Rightarrow \quad \underline{Z} = \frac{\underline{U}}{\underline{I}}$$
  
The voltage  $\underline{U} = 3.0 \cdot e^{j(2\pi \cdot 15 \cdot t)}$  V and the current  $\underline{I} = 0.24 \cdot e^{j(2\pi \cdot 15 \cdot t - \varphi)}$  A are given. The resulting impedance  $\underline{Z}$  is  $\underline{Z} = \frac{3.0}{0.24} \cdot e^{j\varphi} = 12.5 \cdot e^{j\varphi} \Omega$ .

Therefore, the component  $Z$  is a pure inductor with the same absolute value of  $12.5 \Omega$  and a phase shift  $\varphi = \varphi_u - \varphi_i = 0 - (-\varphi) = \varphi$ .

$$\underline{Z} = R + jX_L = 10 + j1.88 \Omega$$
  
The absolute value  $|Z| = \sqrt{10^2 + 1.88^2} = 10.18 \Omega$  and the phase shift  $\varphi = \arctan\left(\frac{1.88}{10}\right) = 10.73^\circ$ .

With the complex part  $\varphi = 10.73^\circ$  and  $|Z| = 10.18 \Omega$ , the impedance  $\underline{Z}$  is  $\underline{Z} = 10.18 \cdot e^{j10.73^\circ} \Omega$ .

The phase shift  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{1.88}{10}\right) = 10.73^\circ$ .

### Exercise E14 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the complex impedance  $Z$  of the circuit shown in the figure. The voltage  $u(t) = 3.0 \cdot \sin(2\pi \cdot 15 \cdot t)$  V and the current  $i(t) = 0.24 \cdot \sin(2\pi \cdot 15 \cdot t - \varphi)$  A shall be given.

After analysis, the following dimensions must be provided:  $Z$  in  $\Omega$ ,  $\varphi$  in degrees. The phase shift  $\varphi$  is defined as  $\varphi = \varphi_u - \varphi_i$ .

Solution  
Result  
.. Draw the circuit diagram of the given circuit.  
Solution  $Z = 10.18 \cdot e^{j10.73^\circ} \Omega$

With the complex part  $\varphi = 10.73^\circ$  and  $|Z| = 10.18 \Omega$ , the impedance  $\underline{Z}$  is  $\underline{Z} = 10.18 \cdot e^{j10.73^\circ} \Omega$ .

The phase shift  $\varphi$  can be calculated as  $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{1.88}{10}\right) = 10.73^\circ$ .





**Exercise E12 Impedances at different Frequencies**  
**(written test, approx. 18 % of a 60-minute written test, WS2022)**

2. A series circuit consists of a resistor with a resistance of  $R_1 = 1.00 \text{ k}\Omega$ , a capacitor with a capacitance of  $C_1 = 40 \text{ nF}$ , and an inductor with an inductance of  $L_1 = 4.7 \text{ }\mu\text{H}$ . The circuit is connected to an AC voltage source with a voltage of  $U = 10 \text{ V}$  and a frequency of  $f = 4 \text{ MHz}$ . Calculate the absolute value of the impedance  $|Z|$  of the circuit.

Solution

$$|Z| = \sqrt{R_1^2 + (X_L - X_C)^2}$$

$$|Z| = \sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}$$

A series circuit means that the current is constant on every component.  
 The equivalent impedance for  $R$  and  $L$  combined is given by  $Z = R + jX_L$   
 Parallel circuit means that the voltage is the same on  $R$  and  $C$   $Z = \frac{R \cdot X_C}{R + jX_C}$   
 $|Z| = \sqrt{R^2 + X_L^2}$  since  $X_L$  and  $X_C$  are perpendicular  
 $|Z| = \sqrt{R^2 + (X_L - X_C)^2}$  since  $X_L$  and  $X_C$  are perpendicular  
 $|Z| = \sqrt{R^2 + (2\pi \cdot f \cdot L - \frac{1}{2\pi \cdot f \cdot C})^2}$  (It has to, since  $R$  is perpendicular to  $X_L$  and  $X_C$  too)  
 Therefore, the resulting current of the parallel circuit is given as:  
 $I = \frac{U}{|Z|} = \frac{10 \text{ V}}{\sqrt{(1.00 \text{ k}\Omega)^2 + (2\pi \cdot 4 \text{ MHz} \cdot 4.7 \text{ }\mu\text{H} - \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}})^2}}$   
 $I = 1.00 \text{ mA}$   
 Back to the first formula:  $R \cdot I = X_C \cdot I$   
 $R = X_C \cdot \frac{I}{I} = \frac{X_C \cdot I}{I} = \frac{1}{2\pi \cdot f \cdot C} \cdot \frac{I}{I} = \frac{1}{2\pi \cdot f \cdot C}$

**Exercise E1 Resistance of a Wire by Resistivity**  
**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A heating element made of nichrome wire with a diameter of  $d = 0.35 \text{ mm}$  and a length of  $l = 3 \text{ m}$  is used for heating. The power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary. Calculate the resistance  $R$  of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot l \cdot \frac{1}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad \& \quad R = \rho \cdot l \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ &= 1.10 \cdot 10^{-6} \cdot \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \cdot \text{m}}{(3.57 \cdot 10^{-3} \cdot \text{m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$


**Exercise E8 Charging Capacitors**  
 (written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (with the light bulb) also consists of a DC voltage source  $U = 12 \text{ V}$ , a resistor  $R_1 = 20 \text{ }\Omega$ , a capacitor  $C = 100 \text{ }\mu\text{F}$ , and a light bulb  $R_B = 5 \text{ }\Omega$ . The switch  $S_1$  is open. The voltage across the capacitor is again  $0 \text{ V}$  at the moment  $t_0 = 0 \text{ s}$  when the switch  $S_1$  is closed. Calculate the voltage  $u_c(t_2)$  across the capacitor at  $t_2 = 1 \text{ ms}$  after closing the switch.

**Solution**  
 Hint: To solve this, first create an equivalent linear voltage source from  $U$ ,  $R_1$ , and  $R_B$ .

**Solution**  
 The ideal voltage source  $U$  is in series with  $R_1$  and  $R_B$ . The voltage  $u_c$  is independent of this series combination.


On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting  $S_1$ .



The circuit contains a voltage source  $U = 12 \text{ V}$ , a switch  $S_1$ , a resistor of  $R_1 = 20 \text{ }\Omega$  and a capacitor of  $C = 100 \text{ }\mu\text{F}$ . The switch  $S_2$  to an additional consumer  $R_2$  will be considered to be open for the first tasks. At the moment  $t_0 = 0 \text{ s}$  the switch  $S_1$  is closed, the voltage across the capacitor is  $u_c(t_0) = 0 \text{ V}$ .

... First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time  $t_1$  when  $u_c(t_1) = 0.5 \cdot U$ .

**Solution**



An equivalent linear voltage source can be given with  $U_s$ ,  $R_1$ , and  $R_B$  as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is:  $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$  The internal resistance is given by substituting the ideal voltage source with its resistance ( $R = 0 \Omega$ , short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t) = U_s \cdot (1 - e^{-t/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-t/(10 \Omega \cdot 100 \mu F)})$$

The following formula describes the time course of  $u_c(t)$  which has to be  $u_c(t_1) = 0.5 \cdot U$ : 
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to  $(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies t/\tau = \ln(0.5) \implies t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$



**Exercise E4 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)**

The following shall be solved at once,  $R_1 = R_2 = R_3 = 10 \Omega$  and the voltage  $U = 10V$  is given.  $R_B$ .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since  $R_2=R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \text{ } \Omega)^2}{3 \cdot 100 \text{ } \Omega} = \frac{1}{3} \cdot 100 \text{ } \Omega = 33.33 \text{ } \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \text{ } \Omega + (33.33 \text{ } \Omega + 400 \text{ } \Omega) \parallel (33.33 \text{ } \Omega + 100 \text{ } \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between  $A$  and  $B$ .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = \{500 \sim \Omega \cdot 200 \sim \Omega\} \over {500 \sim \Omega + 200 \sim \Omega}$$

From:

<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

[https://first.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/ws2022\\_exam?rev=1680241381](https://first.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680241381)

Last update: **2023/03/31 07:43**

