

# task\_elndbo3xwi2klxuu\_with\_calculation

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

Exercise E16 Lorentz Force (hard!) (written test, approx. 10 % of a 120-minute written test, SS2021) ..... 2

## lorentz force, exam ee2 SS2021

### Exercise E16 Lorentz Force (hard!)

(written test, approx. 10 % of a 120-minute written test, SS2021)

A) The picture below shows a straight high voltage direct current transmission line with a current of  $I = 2000 \text{ A}$  flowing into the page. The resulting force is? (Independent)

A homogeneous geomagnetic field is assumed. The magnetic field strength has a vertical component of  $B_{\text{v}} = 40 \text{ } \mu\text{T}$  and a horizontal component of  $B_{\text{h}} = 20 \text{ } \mu\text{T}$ .

Only a force of  $7 \text{ N}$  is perpendicular to  $\vec{B}_{\text{v}}$  and to  $\vec{I}$  and points in the right direction by the right-hand rule.

The picture on the right shows the line (black), the field strength components, and the angle in front and top view for illustration purposes.

Top View

— — — —

Path

a) Calculate the force that results from the current flow on the entire conductor.

First, calculate the vertical and horizontal components and combine them accordingly.

Path

- The horizontal component  $\vec{F}_{\text{h}}$  of the force is based on the vertical component  $\vec{B}_{\text{v}}$  of the magnetic field.
- The vertical component  $\vec{B}_{\text{v}}$  of the magnetic field is not shown in the image but is pointing into the ground.
- It has to be perpendicular to  $\vec{B}_{\text{v}}$  and to  $\vec{I}$ . The right-hand rule has to be applied.

The force on the transmission line can be calculated via the Lorentz force

$$\vec{F}_{\text{L}} = I \cdot \vec{l} \times \vec{B}$$

\end{align\*}

Here, we have two components for the current - and therefore for the force - to evaluate.

Considering the right-hand rule (and the cross product), the vertical field  $B_{\rm v}$  generates a horizontal force  $F_{\rm h}$  and vice versa.


The **horizontal component** is given by



$$\begin{aligned} F_{\text{h}} &= l \cdot (l \cdot B_{\text{v}}) \quad \&= 1'200 \text{ A} \cdot 300 \\ &\quad \cdot 10^3 \text{ m} \cdot 40 \cdot 10^{-6} \left\{ \frac{\text{Vs}}{\text{m}^2} \right\} \quad \&= 14'400 \\ &\quad \text{VA} = 14'400 \text{ V} \quad \&= 14'400 \text{ N} \end{aligned}$$

For the **vertical component** the angle  $\alpha$  has to be considered.

For the maximum  $F_{\text{v}}$  the angle  $\alpha$  has to be  $90^\circ$ , therefore the  $\sin$  has to be used.



$$\begin{aligned} F_{\text{v}} &= l \cdot l \cdot B_{\text{h}} \cdot \sin \alpha \quad \&= 1'200 \\ &\quad \text{A} \cdot 300 \cdot 10^3 \text{ m} \cdot 40 \cdot 10^{-6} \left\{ \frac{\text{Vs}}{\text{m}^2} \right\} \cdot \sin 20^\circ \quad \&= 2'462.545... \text{ N} \end{aligned}$$

For the **overall force**  $F$  the Pythagorean theorem has to be used:

$$F = \sqrt{F_{\text{v}}^2 + F_{\text{h}}^2} \quad \&= \sqrt{(14'400 \text{ N})^2 + (2'462.545... \text{ N})^2} \quad \&= 14'609.04... \text{ N}$$

From:  
<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:  
[https://first.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_elndbo3xwi2klxuu\\_with\\_calculation](https://first.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_elndbo3xwi2klxuu_with_calculation)

Last update: **2024/07/03 15:21**

