

task_unkkahm3u0v9azny_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E12 Self Induction (written test, approx. 8 % of a 120-minute written test, SS2022)

..... 2

self induction, induction, exam ee2 SS2022

Exercise E12 Self Induction

(written test, approx. 8 % of a 120-minute written test, SS2022)

2. A motor is in a motion with a magnitude of $\Delta i = 50$, which the circuit breaker has a DC voltage source U_{ind} which is fused with a circuit breaker.

Sketch the diagram $i(t)$ and $u_{\text{ind}}(t)$ with the circuit breaker $U_{\text{ind}} = 63$ A and the induced voltage U_{ind} linearly down to 0 A within 1 μ s.

(The inner resistance of the motor shall be neglected.)

$$u_{\text{ind}}(t) = 3150 \text{ V}$$

Path

.. Draw the circuit (the circuit breaker can be drawn as a switch), with all voltage and current arrows.

For the maximum voltage on the circuit breaker one has to consider the following:


Result

- external voltage of the voltage source U_{ind}
- voltage $u_{\text{ind}}(t)$ induced by the change of the current

The first one is not given in the exercise, and therefore not considered here.

The induced voltage can be calculated by linearizing the following:
$$u_{\text{ind}}(t) = -L \frac{di}{dt} \rightarrow u_{\text{ind}}(t) = -L \frac{\Delta i}{\Delta t}$$

With the given details:
$$u_{\text{ind}}(t) = -L \frac{0 - I}{t_1 - t_0} = 50 \cdot 10^{-6} \cdot \frac{63 \text{ A}}{1 \cdot 10^{-6} \text{ s}} = 3150 \frac{\text{Vs}}{\text{A}} \cdot \frac{\text{A}}{\text{s}}$$



From:

<https://first.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://first.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_unkkahm3u0v9azny_with_calculation

Last update: **2024/07/05 03:25**

