

rechnung_signalzeitverlauf_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$I.\quad\$ Am Punkt \$t_1\$

$U_A(t_1) = - \frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$	
$U_A(t_1) = - \frac{1}{5 \text{ ms}} \cdot \int_0^{10 \text{ ms}} 1 \text{ V} \, dt + 0 \text{ V}$	
$U_A(t_1) = - \frac{1}{5 \text{ ms}} \cdot 1 \text{ V} \cdot 10 \text{ ms} + 0 \text{ V}$	
$U_A(t_1) = -2 \text{ V}$	
$U_A(t_1) = -2 \text{ V}$	
$U_A(t_1) = -2 \text{ V}$	
$U_A(t_1) = -2 \text{ V}$	

\$I.\quad\$ Am Punkt \$t_2\$

$U_A(t_1) = - \frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$	
$U_A(t_1) = - \frac{1}{5 \text{ ms}} \cdot \int_0^{20 \text{ ms}} (-1 \text{ V}) \, dt + 2 \text{ V}$	
$U_A(t_1) = 0 \text{ V}$	
$U_A(t_1) = 0 \text{ V}$	

\$I.\quad\$ Am Punkt \$t_3\$

$U_A(t_1) = - \frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$	
$U_A(t_1) = - \frac{1}{5 \text{ ms}} \cdot \int_0^{20 \text{ ms}} (-2 \text{ V}) \, dt + 0 \text{ V}$	
$U_A(t_1) = -2 \text{ V}$	
$U_A(t_1) = -2 \text{ V}$	

From:
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://first.mexle.te.hs-heilbronn.de/elektronische_schaltungstechnik/rechnung_signalzeitverlauf_umkehrintegrator?rev=1590080530

Last update: 2021/05/09 09:53

