

Photodiode as current source

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Photo Diode as current source 2

Photo Diode as current source



Fig. 2: Inverting Op-Amp: Photo Diode BPW 34 S




Fig. 3: Inverting Op-Amp: Diagramms of BPW 34 S



Fig. 4: Inverting Op-Amp: Photo Diode as current source

$$U_{DD} \approx 10\text{V}, U_{SS} \approx -10\text{V}$$

We assume good illuminated room by white led lamp of 300 lx. White light is a mixture of many wavelengths across the visible spectrum, roughly 380 to 780 nm. For a typical white LED, the spectrum usually comes from a blue LED chip with a peak around 450 nm, plus a broader phosphor emission that spreads across green, yellow, and red wavelengths. To make it easier to calculate we take 500 nm (in reality a greenish light) and 300 lx for the illumination.

In figure 3 we can see that the sensitivity of the photo diode at 500 nm ist only 30%. The maximim current (100%) at 300 lx is around 30 μA .

Now we kan calculate the current we expect from the diode at 300 lx:

Complete the arrows in the scematic of the circuit.

Take the values for U_1, U_2, U_{OUT} from .

Use these values to calculate the sum of the voltages at node N_{12} .

Compare your result by measuerement.

$$U_1 \approx$$

$$U_2 \approx$$

$$U_{OUT} \approx$$

Calculated U_{R2}

Measured U_{R2}

What are your results?

\dots

\dots

\dots

What will happen if you short-circuit R_2 ?
Try it and explain your results.

\dots

\dots

\dots

\dots

\dots

\dots

\dots

\dots

\dots

\dots

\dots

From: <https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link: https://first.mexle.te.hs-heilbronn.de/lab05_en/inverting_op-amp_photo_diode_as_current_source?rev=1776426669

Last update: 2026/04/17 13:51

