

Loop law

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Loop law

Node law

2

3

Loop law

Kirchhoff's voltage law: In every closed loop of an electrical network, the sum of all voltages is zero.

Set the voltage on the power supply to 12 V and measure this voltage accurately using a multimeter. Build the measurement circuit shown in [figure 1](#).




Fig. 1: Verification of

Kirchhoff's voltage law

Add the voltage arrows and measure U , U_{1} and U_{2} .

U	U_{1}	U_{2}

Tab. 1: Voltage measurement for Kirchhoff's voltage law

What is the loop equation here?

Verify the equation using the measured values.

The resistors R_{1} and R_{2} connected in series form a voltage divider. In what ratio are the voltages U_{1} and U_{2} ?

$$\frac{U_{\text{1}}}{U_{\text{2}}} =$$

Node law

Kirchhoff's current law: At every node, the sum of all currents flowing into and out of the node is zero.

Set the voltage on the power supply to 12 V and measure the voltage accurately using a multimeter. As a first step, build the measurement circuit shown in [figure 2](#).




Fig. 2: Branch currents for verification of Kirchhoff's current law

Add the arrows indicating the directions of currents I_{1} and I_{2} . On both multimeters, set the DC current range and the polarity before switching on. Then measure currents I_{1} and I_{2} and enter the measured values in the table.




Fig. 3: Total current and node \$K\$

In what ratio are currents $I_{\rm 1}$ and $I_{\rm 2}$?

$\frac{I_{\rm 1}}{I_{\rm 2}} =$

Switch the power supply on again and measure the current I . Enter its value in the table.

I	$I_{\rm 1}$	$I_{\rm 2}$

Tab. 2: Current measurement for Kirchhoff's current law

Determine the node equation for node \$K\$ and verify its validity.

Using the measured values of resistors $R_{\rm 1}$, $R_{\rm 2}$ and $R_{\rm 3}$, calculate the total resistance $R_{\rm KP}$.

Using the calculated value of $R_{\rm KP}$, verify the measured value of the total current:

$$I = \frac{U}{R_{\rm KP}} =$$

From:

<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://first.mexle.te.hs-heilbronn.de/lab_electrical_engineering/1_resistors/mesh-set?rev=1773619858

Last update: **2026/03/16 01:10**

