

Non-linear resistors

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Nonlinear resistors 2

Nonlinear resistors

All resistors examined so far are linear resistors, for which the characteristic curve $I=f(U)$ is a straight line, s. [figure 1](#). The resistance value of a linear resistor is independent of the current I flowing through it or the applied voltage U .




Fig. 1: Characteristic curve of a linear resistor

With nonlinear resistors, there is no proportionality between current and voltage. The characteristic curve of such a resistor is shown in [figure 2](#). With these resistors, we talk about static resistance (R) and dynamic (or differential) resistance (r). The static resistance is determined for a specific operating point: at a specific voltage, the current is read from the resistance characteristic curve. The calculation is performed according to Ohm's law:

$$R = \frac{U}{I}$$

The differential resistance around the operating point is calculated from the current difference caused by a change in the applied voltage:

$$r = \frac{\Delta U}{\Delta I}$$

Fig. 2: Characteristic curve of a nonlinear resistor

A light bulb is examined as an example of a nonlinear resistor. Set up the measuring circuit shown in [figure 3](#).




Fig. 3: Measuring circuit light bulb

Set the voltage on the power supply to the voltage values from [table 1](#). Measure the corresponding current values and enter them in [table 1](#).

U [V]	0.5	1.0	2.0	3.0	4.0	5.0	6.0	7.0	8.0
I [mA]									

Tab. 1: Values characteristic curve light bulb

Create the characteristic curve $I = f(U)$, s. figure ##




Fig. ##: Characteristic curve light bulb

Calculate the static resistance R at the operating point $U = \text{7.0 V}$:

Calculate the dynamic resistance r at the operating point $U = \text{7.0 V}$:

Compare the values with the values from table ## (direct resistance measurement)

From:
<https://first.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://first.mexle.te.hs-heilbronn.de/lab_electrical_engineering/1_resistors/nonlinear-resistors?rev=1773110434

Last update: 2026/03/10 03:40

